

AN13736

Using IMX-OS08A20 Camera Module on i.MX 8M Plus Evaluation Kit

Rev. 0 — 20 September 2022

Application note

Document information

Information	Content
Keywords	AN13736, i.MX 8M Plus Evaluation Kit (i.MX 8M Plus EVK), IMX-OS08A20 accessory card, MIPI-CSI interface camera kit, Machine vision, 4K camera
Abstract	This document provides a brief overview on how to get started with the IMX-OS08A20 accessory card and the i.MX 8M Plus EVK.



1 Introduction

NXP provides optional accessory boards that can be used to evaluate the i.MX 8M Plus EVK. The IMX-OS08A20 for the i.MX 8M Plus EVK is a MIPI-CSI interface camera kit based on OmniVision chipset OS08A20. The IMX-OS08A20 camera module can be purchased from [4K MIPI CMOS Camera Module](#) product page.

This document provides a brief overview on how to get started with the IMX-OS08A20 accessory card and the i.MX 8M Plus EVK.

Key specifications / features:

- Image sensor optical size of 1/2" with 8 megapixels (3840*2160)
- Supported output formats: 12-/10-bit RAW RGB
- Maximum image transfer rate:
 - 4K2K (3840*2160): 60 fps
 - 1080 p (1920*1080): 120 fps
 - 720p (1280*720): 180 fps

2 Get to know the IMX-OS08A20 accessory card

IMX-OS08A20 accessory card contains a bridge card and a camera module. The camera module is connected to the bridge card through a connector that is assembled during the manufacturing phase.

Table 1. Items in IMX-OS08A20 accessory

Item	Quantity
Camera module	1
8" mini-SAS cable	1



Figure 1. IMX-OS08A20 accessory card

3 How to use the IMX-OS08A20 accessory card

This section describes quick steps to get started with the IMX-OS08A20 accessory card.

Note: Before plugging in the cable, remove the plastic cover on the mini-SAS connectors.

3.1 Hardware setup

To enable IMX-OS08A20 camera module, follow the steps below:

1. Plugin the mini-SAS cable into the mini-SAS connector on the IMX-OS08A20 accessory card.
2. Plugin the other end of the mini-SAS cable into J12 on the i.MX 8M Plus EVK.

Figure 2. Hardware setup of IMX-OS08A20 accessory card



3.2 Software setup: Linux

The default Board Support Package (BSP) supports the MIPI-CSI on J12. To enable the camera on J12, replace the original *.dtb file with imx8mp-evk-os08a20.dtb file as follows.

```
U-Boot > setenv fdtfile imx8mp-evk-os08a20.dtb
U-Boot > saveenv
U-Boot > boot
```

The camera GStreamer commands are:

```
gst-launch-1.0 -v v4l2src device=/dev/video2 ! "video/x-raw,format=YUY2,width=1920,height=1080" ! queue ! waylandsink
```

```
gst-launch-1.0 -v v4l2src device=/dev/video2 ! "video/x-raw,format=YUY2,width=3840,height=2160" ! queue ! waylandsink
```

4 References

[Table 2](#) provides the link to access software or order the evaluation kit and accessory boards.

Table 2. Link to access software/order evaluation kit

Compatible boards	Description	Link
8MPLUSLPD4-EVK	i.MX 8M Plus Evaluation Kit	Evaluation Kit for the i.MX 8M Plus Applications Processor

For latest software, see [i.MX Software and Development Tools](#).

5 Revision history

[Table 3](#) summarizes the changes done to this document since the initial release.

Table 3. Revision history

Revision number	Date	Substantive changes
0	20 September 2022	Initial release

6 Legal information

6.1 Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

6.2 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Suitability for use in non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at PSIRT@nxp.com) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

6.3 Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

NXP — wordmark and logo are trademarks of NXP B.V.

Contents

1	Introduction	2
2	Get to know the IMX-OS08A20 accessory card	2
3	How to use the IMX-OS08A20 accessory card	3
3.1	Hardware setup	3
3.2	Software setup: Linux	3
4	References	4
5	Revision history	4
6	Legal information	5

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[NXP:](#)

[IMX-OS08A20](#)