

# 64-pin CK505 for Desktop Systems

# ICS9LP505-1

## Recommended Application:

CK505 clock, 64-pin Intel Yellow Cover part

## Output Features:

- 2 - CPU differential low power push-pull pairs
- 10 - SRC differential low power push-pull pairs
- 1 - CPU/SRC selectable differential low power push-pull pair
- 1 - SRC/DOT selectable differential low power push-pull pair
- 5 - PCI, 33MHz
- 1 - PCI\_F, 33MHz free running
- 1 - USB, 48MHz
- 1 - REF, 14.318MHz

## Key Specifications:

- CPU outputs cycle-cycle jitter < 85ps
- SRC output cycle-cycle jitter < 125ps
- PCI outputs cycle-cycle jitter < 500ps
- +/- 100ppm frequency accuracy on CPU & SRC clocks

## Features/Benefits:

- Supports spread spectrum modulation, default is 0.5% down spread
- Uses external 14.318MHz crystal, external crystal load caps are required for frequency tuning
- Selectable SRC differential push-pull pair/two single-ended outputs

## Pin Configuration

|                |    |    |                    |
|----------------|----|----|--------------------|
| PCI0/CR#_A     | 1  | 64 | SCLK               |
| VDDPCI         | 2  | 63 | SDATA              |
| PCI1/CR#_B     | 3  | 62 | REF0/FSLC/TEST_SEL |
| PCI2/TME       | 4  | 61 | VDDREF             |
| PCI3           | 5  | 60 | X1                 |
| PCI4/SRC5_EN   | 6  | 59 | X2                 |
| PCI_F5/ITP_EN  | 7  | 58 | GNDREF             |
| GNDPCI         | 8  | 57 | FSLB/TEST_MODE     |
| VDD48          | 9  | 56 | CK_PWRGD/PD#       |
| USB_48MHz/FSLA | 10 | 55 | VDDCPU             |
| GND48          | 11 | 54 | CPUT0              |
| VDD96_IO       | 12 | 53 | CPUC0              |
| DOTT_96/SRCT0  | 13 | 52 | GNDCPU             |
| DOTC_96/SRCC0  | 14 | 51 | CPUT1_F            |
| GND            | 15 | 50 | CPUC1_F            |
| VDD            | 16 | 49 | VDDCPU_IO          |
| SRCT1/SE1      | 17 | 48 | VOUT               |
| SRCC1/SE2      | 18 | 47 | CPUT2_ITP/SRCT8    |
| GND            | 19 | 46 | CPUC2_ITP/SRCC8    |
| VDDPLL3_IO     | 20 | 45 | VDDSRC_IO          |
| SRCT2/SATAT    | 21 | 44 | SRCT7/CR#_F        |
| SRCC2/SATAC    | 22 | 43 | SRCC7/CR#_E        |
| GNDSRC         | 23 | 42 | GNDSRC             |
| SRCT3/CR#_C    | 24 | 41 | SRCT6              |
| SRCC3/CR#_D    | 25 | 40 | SRCC6              |
| VDDSRC_IO      | 26 | 39 | VDDSRC             |
| SRCT4          | 27 | 38 | PCI_STOP#/SRCT5    |
| SRCC4          | 28 | 37 | CPU_STOP#/SRCC5    |
| GNDSRC         | 29 | 36 | VDDSRC_IO          |
| SRCT9          | 30 | 35 | SRCC10             |
| SRCC9          | 31 | 34 | SRCT10             |
| SRCC11/CR#_G   | 32 | 33 | SRCT11/CR#_H       |

9LP505-1

### 64-TSSOP

- \* Internal Pull-Up Resistor
- \*\* Internal Pull-Down Resistor

**Table 1: CPU Frequency Select Table**

| FS <sub>L</sub> C <sup>2</sup><br>B0b7 | FS <sub>L</sub> B <sup>1</sup><br>B0b6 | FS <sub>L</sub> A <sup>1</sup><br>B0b5 | CPU<br>MHz | SRC<br>MHz | PCI<br>MHz | REF<br>MHz | USB<br>MHz | DOT<br>MHz |
|----------------------------------------|----------------------------------------|----------------------------------------|------------|------------|------------|------------|------------|------------|
| 0                                      | 0                                      | 0                                      | 266.66     | 100.00     | 33.33      | 14.318     | 48.00      | 96.00      |
| 0                                      | 0                                      | 1                                      | 133.33     |            |            |            |            |            |
| 0                                      | 1                                      | 0                                      | 200.00     |            |            |            |            |            |
| 0                                      | 1                                      | 1                                      | 166.66     |            |            |            |            |            |
| 1                                      | 0                                      | 0                                      | 333.33     |            |            |            |            |            |
| 1                                      | 0                                      | 1                                      | 100.00     |            |            |            |            |            |
| 1                                      | 1                                      | 0                                      | 400.00     |            |            |            |            |            |
| 1                                      | 1                                      | 1                                      | Reserved   |            |            |            |            |            |

1. FS<sub>L</sub>A and FS<sub>L</sub>B are low-threshold inputs. Please see V<sub>IL\_FS</sub> and V<sub>IH\_FS</sub> specifications in the Input/Supply/Common Output Parameters Table for correct values. Also refer to the Test Clarification Table.
2. FS<sub>L</sub>C is a three-level input. Please see the V<sub>IL\_FS</sub> and V<sub>IH\_FS</sub> specifications in the Input/Supply/Common Output Parameters Table for correct values.

## Pin Description

| PIN # | PIN NAME       | TYPE | DESCRIPTION                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|-------|----------------|------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1     | PCI0/CR#_A     | I/O  | 3.3V PCI clock output or Clock Request control A for either SRC0 or SRC2 pair<br>The power-up default is PCI0 output, but this pin may also be used as a Clock Request control of SRC pair 0 or SRC pair 2 via SMBus. Before configuring this pin as a Clock Request Pin, the PCI output must first be disabled in byte 2, bit 0 of SMBus address space. After the PCI output is disabled (high-Z), the pin can then be set to serve as a Clock Request pin for either SRC pair 2 or pair 0 using the CR#_A_EN bit located in byte 5 of SMBUs address space.<br><b>Byte 5, bit 7</b><br>0 = PCI0 enabled (default)<br>1 = CR#_A enabled. Byte 5, bit 6 controls whether CR#_A controls SRC0 or SRC2 pair<br><b>Byte 5, bit 6</b><br>0 = CR#_A controls SRC0 pair (default),<br>1 = CR#_A controls SRC2 pair |
| 2     | VDDPCI         | PWR  | Power supply pin for the PCI outputs, 3.3V nominal                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 3     | PCI1/CR#_B     | I/O  | 3.3V PCI clock output/Clock Request control B for either SRC1 or SRC4 pair<br>The power-up default is PCI1 output, but this pin may also be used as a Clock Request control of SRC pair 1 or SRC pair 4 via SMBus. Before configuring this pin as a Clock Request Pin, the PCI output must first be disabled in byte 2, bit 1 of SMBus address space. After the PCI output is disabled (high-Z), the pin can then be set to serve as a Clock Request pin for either SRC pair 1 or pair 4 using the CR#_B_EN bit located in byte 5 of SMBUs address space.<br><b>Byte 5, bit 5</b><br>0 = PCI1 enabled (default)<br>1 = CR#_B enabled. Byte 5, bit 6 controls whether CR#_B controls SRC1 or SRC4 pair<br><b>Byte 5, bit 4</b><br>0 = CR#_B controls SRC1 pair (default)<br>1 = CR#_B controls SRC4 pair     |
| 4     | PCI2/TME       | I/O  | 3.3V PCI clock output / Trusted Mode Enable (TME) Latched Input. This pin is sampled on power-up as follows<br>0 = Overclocking of CPU and SRC Allowed<br>1 = Overclocking of CPU and SRC <u>NOT</u> allowed<br>After being sampled on power-up, this pin becomes a 3.3V PCI Output                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| 5     | PCI3           | OUT  | 3.3V PCI clock output.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 6     | PCI4/SRC5_EN   | I/O  | 3.3V PCI clock output / SRC5 pair or PCI_STOP#/CPU_STOP# enable strap. On powerup, the logic value on this pin determines if the SRC5 pair is enabled or if CPU_STOP#/PCI_STOP# is enabled (pins 29 and 30). The latched value controls the pin function on pins 29 and 30 as follows<br>0 = PCI_STOP#/CPU_STOP#<br>1 = SRC5/SRC5#                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 7     | PCI_F5/ITP_EN  | I/O  | Free running PCI clock output and ITP/SRC8 enable strap. This output is not affected by the state of the PCI_STOP# pin. On powerup, the state of this pin determines whether pins 38 and 39 are an ITP or SRC pair.<br>0 = SRC8/SRC8#<br>1 = ITP/ITP#                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 8     | GNDPCI         | PWR  | Ground for PCI clocks.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 9     | VDD48          | PWR  | Power supply for USB clock, nominal 3.3V.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| 10    | USB_48MHz/FSLA | I/O  | Fixed 48MHz USB clock output. 3.3V./ 3.3V tolerant input for CPU frequency selection. Refer to input electrical characteristics for Vil_FS and Vih_FS values.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 11    | GND48          | PWR  | Ground pin for the 48MHz outputs.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| 12    | VDD96_IO       | PWR  | Power supply for DOT96 clocks, nominal 0.8V from source/emitter of external pass transistor.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 13    | DOTT_96/SRCT0  | OUT  | True clock of SRC or DOT96. The power-up default function is SRC0. After powerup, this pin function may be changed to DOT96 via SMBus Byte 1, bit 7 as follows:<br>0= SRC0<br>1=DOT96                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 14    | DOTC_96/SRCC0  | OUT  | Complement clock of SRC or DOT96. The power-up default function is SRC0#. After powerup, this pin function may be changed to DOT96# via SMBus Byte 1, bit 7 as follows<br>0= SRC0#<br>1=DOT96#                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 15    | GND            | PWR  | Ground pin for the DOT96 clocks.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| 16    | VDD            | PWR  | Power supply for SRC / SE1 and SE2 clocks, 3.3V nominal.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |

## Pin Description (Continued)

| PIN # | PIN NAME     | TYPE | DESCRIPTION                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|-------|--------------|------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 17    | SRCT1/SE1    | OUT  | True clock of differential SRC1 clock pair / 3.3V single-ended output. The powerup default is 100 MHz SRC, -0.5% downspread. The pin function may be changed via SMBus B1b[4:1]                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 18    | SRCC1/SE2    | OUT  | Complement clock of differential SRC1 clock pair / 3.3V single-ended output. The powerup default is 100 MHz SRC, -0.5% downspread. The pin function may be changed via SMBus B1b[4:1]                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 19    | GND          | PWR  | Ground pin for SRC / SE1 and SE2 clocks, PLL3.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 20    | VDDPLL3_IO   | PWR  | Power supply for PLL3. 0.8V nominal from source/emitter of external pass transistor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| 21    | SRCT2/SATAT  | OUT  | True clock of differential SRC/SATA clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 22    | SRCC2/SATAC  | OUT  | Complement clock of differential SRC/SATA clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 23    | GNDSRC       | PWR  | Ground pin for SRC clocks.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 24    | SRCT3/CR#_C  | I/O  | True clock of differential SRC clock pair/ Clock Request control C for either SRC0 or SRC2 pair<br>The power-up default is SRCCLK3 output, but this pin may also be used as a Clock Request control of SRC pair 0 or SRC pair 2 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC3 output must first be disabled in byte 4, bit 7 of SMBus address space . After the SRC3 output is disabled, the pin can then be set to serve as a Clock Request pin for either SRC pair 2 or pair 0 using the CR#_C_EN bit located in byte 5 of SMBUs address space.<br>Byte 5, bit 3<br>0 = SRC3 enabled (default)<br>1= CR#_C enabled. Byte 5, bit 2 controls whether CR#_C controls SRC0 or SRC2 pair<br>Byte 5, bit 2<br>0 = CR#_C controls SRC0 pair (default),<br>1= CR#_C controls SRC2 pair          |
| 25    | SRCC3/CR#_D  | I/O  | Complementary clock of differential SRC clock pair/ Clock Request control D for either SRC1 or SRC4 pair<br>The power-up default is SRCCLK3 output, but this pin may also be used as a Clock Request control of SRC pair 1 or SRC pair 4 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC3 output must first be disabled in byte 4, bit 7 of SMBus address space . After the SRC3 output is disabled, the pin can then be set to serve as a Clock Request pin for either SRC pair 1 or pair 4 using the CR#_D_EN bit located in byte 5 of SMBUs address space.<br>Byte 5, bit 1<br>0 = SRC3 enabled (default)<br>1= CR#_D enabled. Byte 5, bit 0 controls whether CR#_D controls SRC1 or SRC4 pair<br>Byte 5, bit 0<br>0 = CR#_D controls SRC1 pair (default),<br>1= CR#_D controls SRC4 pair |
| 26    | VDDSRC_IO    | PWR  | Power supply for SRC clocks. 0.8V nominal from source/emitter of external pass transistor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| 27    | SRCT4        | I/O  | True clock of differential SRC clock pair 4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| 28    | SRCC4        | I/O  | Complement clock of differential SRC clock pair 4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| 29    | GNDSRC       | PWR  | Ground pin for SRC clocks.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 30    | SRCT9        | OUT  | True clock of differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 31    | SRCC9        | OUT  | Complement clock of differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| 32    | SRCC11/CR#_G | I/O  | SRC11 complement /Clock Request control for SRC9 pair<br>The power-up default is SRC11#, but this pin may also be used as a Clock Request control of SRC9 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC11 output pair must first be disabled in byte 3, bit 7 of SMBus configuration space After the SRC11 output is disabled (high-Z), the pin can then be set to serve as a Clock Request for SRC9 pair using byte 6, bit 5 of SMBus configuration space<br><b>Byte 6, bit 5</b><br>0 = SRC11# enabled (default)<br>1= CR#_G controls SRC9                                                                                                                                                                                                                                               |

Pin Description (Continued)

| PIN # | PIN NAME        | TYPE | DESCRIPTION                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
|-------|-----------------|------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 33    | SRCT11/CR#_H    | I/O  | <p>SRCT11 true or Clock Request control H for SRC10 pair</p> <p>The power-up default is SRC11, but this pin may also be used as a Clock Request control of SRC10 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC11 output pair must first be disabled in byte 3, bit 6 of SMBus configuration space. After the SRC11 output is disabled (high-Z), the pin can then be set to serve as a Clock Request for SRC10 pair using byte 6, bit 4 of SMBus configuration space</p> <p>Byte 6, bit 4<br/>0 = SRC11 enabled (default)<br/>1 = CR#_H controls SRC10.</p>      |
| 34    | SRCT10          | OUT  | True clock of differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 35    | SRCC10          | OUT  | Complement clock of differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| 36    | VDDSRC_IO       | PWR  | Power supply for SRC clocks. 0.8V nominal from source/emitter of external pass transistor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 37    | CPU_STOP#/SRCC5 | I/O  | <p>Stops all CPU Clocks, except those set to be free running clocks /</p> <p>Complement clock of differential SRC pair. The function of this pin is set up by the power-up strap on pin 6, PCI4/SRC5_EN. The logic value sampled on pin 6 at power-up sets the function as follows:</p> <p>0= CPU_STOP#<br/>1 = SRC5</p> <p>In AMT mode 3 bits are shifted in from the ICH to set the FSC, FSB, FSA values</p>                                                                                                                                                                           |
| 38    | PCI_STOP#/SRCT5 | I/O  | <p>Stops all PCI Clocks, except those set to be free running clocks /</p> <p>Complement clock of differential SRC pair. The function of this pin is set up by the power-up strap on pin 6, PCI4/SRC5_EN. The logic value sampled on pin 6 at power-up sets the function as follows:</p> <p>0= PCI_STOP#<br/>1 = SRC5#</p> <p>In AMT mode, this pin is a clock input which times the FSC, FSB, FSA bits shifted in on pin 37.</p>                                                                                                                                                         |
| 39    | VDDSRC          | PWR  | VDD pin for SRC Pre-drivers, 3.3V nominal                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 40    | SRCC6           | OUT  | Complement clock of low power differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 41    | SRCT6           | OUT  | True clock of low power differential SRC clock pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 42    | GNDSRC          | PWR  | Ground for SRC clocks                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| 43    | SRCC7/CR#_E     | I/O  | <p>SRCT7 complement or Clock Request control E for SRC6 pair</p> <p>The power-up default is SRC7#, but this pin may also be used as a Clock Request control of SRC6 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC7 output pair must first be disabled in byte 3, bit 3 of SMBus configuration space. After the SRC output is disabled (high-Z), the pin can then be set to serve as a Clock Request for SRC6 pair using byte 6, bit 7 of SMBus configuration space</p> <p><b>Byte 6, bit 7</b><br/>0 = SRC7# enabled (default)<br/>1 = CR#_E controls SRC6.</p> |
| 44    | SRCT7/CR#_F     | I/O  | <p>SRCT7 true or Clock Request control 8 for SRC8 pair</p> <p>The power-up default is SRC7, but this pin may also be used as a Clock Request control of SRC8 via SMBus. Before configuring this pin as a Clock Request Pin, the SRC7 output pair must first be disabled in byte 3, bit 3 of SMBus configuration space. After the SRC output is disabled (high-Z), the pin can then be set to serve as a Clock Request for SRC8 pair using byte 6, bit 6 of SMBus configuration space</p> <p><b>Byte 6, bit 6</b><br/>0 = SRC7# enabled (default)<br/>1 = CR#_F controls SRC8.</p>        |
| 45    | VDDSRC_IO       | PWR  | Power supply for SRC clocks. 0.8V nominal from source/emitter of external pass transistor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 46    | CPUC2_ITP/SRCC8 | OUT  | <p>Complement clock of low power differential CPU2/Complement clock of differential SRC pair.</p> <p>The function of this pin is determined by the latched input value on pin 7, PCIF5/ITP_EN on powerup. The function is as follows:</p> <p>Pin 7 latched input Value<br/>0 = SRC8#<br/>1 = ITP#</p>                                                                                                                                                                                                                                                                                    |
| 47    | CPUT2_ITP/SRCT8 | OUT  | <p>True clock of low power differential CPU2/True clock of differential SRC pair. The function of this pin is determined by the latched input value on pin 7, PCIF5/ITP_EN on powerup. The function is as follows:</p> <p>Pin 7 latched input Value<br/>0 = SRC8<br/>1 = ITP</p>                                                                                                                                                                                                                                                                                                         |
| 48    | VOOUT           | PWR  | OP Amp comparator output. This pin drives the base/gate of the external pass transistor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |


Pin Description (Continued)

| PIN # | PIN NAME           | TYPE | DESCRIPTION                                                                                                                                                                                                                                                               |
|-------|--------------------|------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 49    | VDDCPU_IO          | PWR  | Supply for CPU clocks. 0.8V nominal from source/emitter of external pass transistor                                                                                                                                                                                       |
| 50    | CPUC1_F            | OUT  | Complement clock of low power differential CPU clock pair. This clock will be free-running during iAMT.                                                                                                                                                                   |
| 51    | CPUT1_F            | OUT  | True clock of low power differential CPU clock pair. This clock will be free-running during iAMT.                                                                                                                                                                         |
| 52    | GNDCPU             | PWR  | Ground Pin for CPU Outputs                                                                                                                                                                                                                                                |
| 53    | CPUC0              | OUT  | Complement clock of low power differential CPU clock pair.                                                                                                                                                                                                                |
| 54    | CPUT0              | OUT  | True clock of low power differential CPU clock pair.                                                                                                                                                                                                                      |
| 55    | VDDCPU             | PWR  | Power Supply 3.3V nominal.                                                                                                                                                                                                                                                |
| 56    | CK_PWRGD/PD#       | IN   | Notifies CK505 to sample latched inputs, or iAMT entry/exit, or PWRDWN# mode                                                                                                                                                                                              |
| 57    | FSLB/TEST_MODE     | IN   | 3.3V tolerant input for CPU frequency selection. Refer to input electrical characteristics for $V_{il\_FS}$ and $V_{ih\_FS}$ values. TEST_MODE is a real time input to select between Hi-Z and REF/N divider mode while in test mode. Refer to Test Clarification Table.  |
| 58    | GNDREF             | PWR  | Ground pin for crystal oscillator circuit                                                                                                                                                                                                                                 |
| 59    | X2                 | OUT  | Crystal output, nominally 14.318MHz.                                                                                                                                                                                                                                      |
| 60    | X1                 | IN   | Crystal input, Nominally 14.318MHz.                                                                                                                                                                                                                                       |
| 61    | VDDREF             | PWR  | Power pin for the REF outputs, 3.3V nominal.                                                                                                                                                                                                                              |
| 62    | REF0/FSLC/TEST_SEL | I/O  | 3.3V 14.318MHz reference clock/3.3V tolerant low threshold input for CPU frequency selection. Refer to input electrical characteristics for $V_{il\_FS}$ and $V_{ih\_FS}$ values/ TEST_SEL: 3-level latched input to enable test mode. Refer to Test Clarification Table. |
| 63    | SDATA              | I/O  | Data pin for SMBus circuitry, 5V tolerant.                                                                                                                                                                                                                                |
| 64    | SCLK               | IN   | Clock pin of SMBus circuitry, 5V tolerant.                                                                                                                                                                                                                                |

**General Description:**

ICS9LP505-1 follows Intel CK505 Yellow Cover for 64-TSSOP device specification. This clock synthesizer provides a single chip solution for next generation Intel processors and Intel chipsets. ICS9LP505-1 is driven with a 14.318MHz crystal. It also provides a tight ppm accuracy output for Serial ATA and PCI-Express support.


**Functional Block Diagram**



**Power Groups**

| Pin Number |            | Description          |                   |
|------------|------------|----------------------|-------------------|
| VDD        | GND        |                      |                   |
| 49         | 52         | CPUCLK               | Low power outputs |
| 55         | 52         | Master Clock, Analog |                   |
| 26, 36, 45 | 23, 29, 42 | SRCCLK               | Low power outputs |
| 39         | 23, 29, 42 |                      | PLL 1             |
| 20         | 19         | PLL3/SE              | Low power outputs |
| 16         | 19         |                      | PLL 3             |
| 12         | 11         | DOT 96Mhz            | Low power outputs |
| 9          | 11         | USB 48               |                   |
| 61         | 58         | Xtal, REF            |                   |
| 2          | 8          | PCICLK               |                   |

### External Pass Transistor Connection for Desktop Applications



**ICS9LP505-1**  
64-pin CK505 for Desktop Systems

**Absolute Maximum Ratings - DC Parameters**

| PARAMETER              | SYMBOL            | CONDITIONS                          | MIN       | MAX | UNITS | Notes |
|------------------------|-------------------|-------------------------------------|-----------|-----|-------|-------|
| Maximum Supply Voltage | VDDxxx            | Supply Voltage                      |           | 4.6 | V     | 7     |
| Maximum Supply Voltage | VDDxxx_IO         | Low-Voltage Differential I/O Supply |           | 3.8 | V     | 7     |
| Maximum Input Voltage  | V <sub>IH</sub>   | 3.3V Inputs                         |           | 4.6 | V     | 4,5,7 |
| Minimum Input Voltage  | V <sub>IL</sub>   | Any Input                           | GND - 0.5 |     | V     | 4,7   |
| Case Temperature       | T <sub>case</sub> |                                     |           | 115 | °C    |       |
| Storage Temperature    | T <sub>s</sub>    | -                                   | -65       | 150 | °C    | 4,7   |
| Input ESD protection   | ESD prot          | Human Body Model                    | 2000      |     | V     | 6,7   |

<sup>1</sup>Guaranteed by design and characterization, not 100% tested in production.

<sup>2</sup>Operation under these conditions is neither implied, nor guaranteed.

<sup>3</sup>Maximum input voltage is not to exceed VDD

**Electrical Characteristics - Input/Supply/Common Output DC Parameters**

| PARAMETER                                     | SYMBOL                  | CONDITIONS                                                                                              | MIN                   | MAX                   | UNITS | Notes |
|-----------------------------------------------|-------------------------|---------------------------------------------------------------------------------------------------------|-----------------------|-----------------------|-------|-------|
| Ambient Operating Temp                        | T <sub>ambient</sub>    | -                                                                                                       | 0                     | 70                    | °C    |       |
| Supply Voltage                                | VDDxxx                  | Supply Voltage                                                                                          | 3.135                 | 3.465                 | V     |       |
| Supply Voltage                                | VDDxxx_IO               | Low-Voltage Differential I/O Supply                                                                     | 0.72                  | 0.9                   | V     | 10    |
| Input High Voltage                            | V <sub>IHSE</sub>       | Single-ended 3.3V inputs                                                                                | 2                     | V <sub>DD</sub> + 0.3 | V     | 3     |
| Input Low Voltage                             | V <sub>ILSE</sub>       | Single-ended 3.3V inputs                                                                                | V <sub>SS</sub> - 0.3 | 0.8                   | V     | 3     |
| Low Threshold Input-High Voltage              | V <sub>IH_FS_TEST</sub> | 3.3 V +/-5%                                                                                             | 2                     | VDD + 0.3             | V     | 8     |
| Low Threshold Input-FSC = '1' Voltage         | V <sub>IH_FS_FSC</sub>  | 3.3 V +/-5%                                                                                             | 0.7                   | 1.5                   | V     | 8     |
| Low Threshold Input-FSA,FSB = '1' Voltage     | V <sub>IH_FS_FSAB</sub> | 3.3 V +/-5%                                                                                             | 0.7                   | VDD+0.3               | V     |       |
| Low Threshold Input-Low Voltage               | V <sub>IL_FS</sub>      | 3.3 V +/-5%                                                                                             | V <sub>SS</sub> - 0.3 | 0.35                  | V     |       |
| PCI3 Input                                    | V <sub>IL_CFGHI</sub>   | Optional input, 2.75V typ.                                                                              | 2.4                   | VDD+0.3               | V     | 9     |
| PCI3 Input                                    | V <sub>IL_CFGMID</sub>  | Optional input, 1.65V typ.                                                                              | 1.3                   | 2                     | V     | 9     |
| PCI3 Input                                    | V <sub>IL_CFGLO</sub>   | Optional input, 0.55V typ.                                                                              | V <sub>SS</sub> - 0.3 | 0.9                   | V     | 9     |
| Input Leakage Current                         | I <sub>IN</sub>         | V <sub>IN</sub> = V <sub>DD</sub> , V <sub>IN</sub> = GND                                               | -5                    | 5                     | uA    | 2     |
| Input Leakage Current                         | I <sub>INRES</sub>      | Inputs with pull up or pull down resistors<br>V <sub>IN</sub> = V <sub>DD</sub> , V <sub>IN</sub> = GND | -200                  | 200                   | uA    |       |
| Output High Voltage                           | V <sub>OHSE</sub>       | Single-ended outputs, I <sub>OH</sub> = -1mA                                                            | 2.4                   |                       | V     | 1     |
| Output Low Voltage                            | V <sub>OLSE</sub>       | Single-ended outputs, I <sub>OL</sub> = 1 mA                                                            |                       | 0.4                   | V     | 1     |
| Operating Supply Current                      | I <sub>DDOP3.3</sub>    | Full Active, C <sub>L</sub> = Full load; I <sub>DD</sub> 3.3V                                           |                       | 200                   | mA    |       |
|                                               | I <sub>DDOPIO</sub>     | Full Active, C <sub>L</sub> = Full load; I <sub>DD</sub> IO                                             |                       | 70                    | mA    | 10    |
| iAMT Mode Current                             | I <sub>DDIAMT3.3</sub>  | M1 mode, 3.3V Rail                                                                                      |                       | 80                    | mA    |       |
|                                               | I <sub>DDIAMTIO</sub>   | M1 Mode, IO Rail                                                                                        |                       | 10                    | mA    |       |
| Powerdown Current                             | I <sub>DDPD3.3</sub>    | Power down mode, 3.3V Rail                                                                              |                       | 5                     | mA    |       |
|                                               | I <sub>DDPDIO</sub>     | Power down mode, IO Rail                                                                                |                       | 0.1                   | mA    | 10    |
| Input Frequency                               | F <sub>I</sub>          | V <sub>DD</sub> = 3.3 V                                                                                 |                       | 15                    | MHz   |       |
| Pin Inductance                                | L <sub>pin</sub>        |                                                                                                         |                       | 7                     | nH    |       |
| Input Capacitance                             | C <sub>IN</sub>         | Logic Inputs                                                                                            | 1.5                   | 5                     | pF    |       |
|                                               | C <sub>OUT</sub>        | Output pin capacitance                                                                                  |                       | 6                     | pF    |       |
|                                               | C <sub>INX</sub>        | X1 & X2 pins                                                                                            |                       | 6                     | pF    |       |
| Clk Stabilization                             | T <sub>STAB</sub>       | From VDD Power-Up or de-assertion of PD to 1st clock                                                    |                       | 1.8                   | ms    |       |
| Tdrive_CR_off                                 | T <sub>DRRCROFF</sub>   | Output stop after CR deasserted                                                                         |                       | 400                   | ns    |       |
| Tdrive_CR_on                                  | T <sub>DRRCRON</sub>    | Output run after CR asserted                                                                            |                       | 0                     | us    |       |
| Tdrive_CPU                                    | T <sub>DRSRC</sub>      | CPU output enable after<br>PCI_STOP# de-assertion                                                       |                       | 10                    | ns    |       |
| Tfall_SE                                      | T <sub>FALL</sub>       | Fall/rise time of all 3.3V control inputs from 20-80%                                                   |                       | 10                    | ns    |       |
| Trise_SE                                      | T <sub>RISE</sub>       |                                                                                                         |                       | 10                    | ns    |       |
| SMBus Voltage                                 | V <sub>DD</sub>         |                                                                                                         | 2.7                   | 5.5                   | V     |       |
| Low-level Output Voltage                      | V <sub>OLSMB</sub>      | @ I <sub>PULLUP</sub>                                                                                   |                       | 0.4                   | V     |       |
| Current sinking at V <sub>OLSMB</sub> = 0.4 V | I <sub>PULLUP</sub>     | SMB Data Pin                                                                                            | 4                     |                       | mA    |       |
| SCLK/SDATA Clock/Data Rise Time               | T <sub>RI2C</sub>       | (Max VIL - 0.15) to<br>(Min VIH + 0.15)                                                                 |                       | 1000                  | ns    |       |
| SCLK/SDATA Clock/Data Fall Time               | T <sub>FI2C</sub>       | (Min VIH + 0.15) to<br>(Max VIL - 0.15)                                                                 |                       | 300                   | ns    |       |
| Maximum SMBus Operating Frequency             | F <sub>SMBUS</sub>      |                                                                                                         |                       | 100                   | kHz   |       |
| Spread Spectrum Modulation Frequency          | f <sub>SSMOD</sub>      | Triangular Modulation                                                                                   | 30                    | 33                    | kHz   |       |

**NOTES ON DC Parameters: (unless otherwise noted, guaranteed by design and characterization, not 100% tested in production).**

<sup>1</sup>Signal is required to be monotonic in this region.

<sup>2</sup>input leakage current does not include inputs with pull-up or pull-down resistors

<sup>3</sup>3.3V referenced inputs are: PCI\_STOP#, CPU\_STOP#, TME, SRC5\_EN, ITP\_EN, SCLKL, SDATA, TESTMODE, TESTSEL, CKPWRGD and CR# inputs if selected.

<sup>4</sup>Intentionally blank

<sup>5</sup>Maximum VIH is not to exceed VDD

<sup>6</sup>Human Body Model

<sup>7</sup>Operation under these conditions is neither implied, nor guaranteed.

<sup>8</sup>Frequency Select pins which have tri-level input

<sup>9</sup>PCI3/CFG0 is optional

<sup>10</sup>If present. Not all parts have this feature.



**AC Electrical Characteristics - Low Power Differential Outputs**

| PARAMETER                  | SYMBOL        | CONDITIONS    | MIN  | MAX  | UNITS | NOTES |
|----------------------------|---------------|---------------|------|------|-------|-------|
| Rising Edge Slew Rate      | $t_{SLR}$     | Averaging on  | 2.5  | 8    | V/ns  | 2, 3  |
| Falling Edge Slew Rate     | $t_{FLR}$     | Averaging on  | 2.5  | 8    | V/ns  | 2, 3  |
| Slew Rate Variation        | $t_{SLVAR}$   | Averaging on  |      | 20   | %     | 1, 10 |
| Differential Voltage Swing | $V_{SWING}$   | Averaging off | 300  |      | mV    | 2     |
| Crossing Point Voltage     | $V_{XABS}$    | Averaging off | 300  | 550  | mV    | 1,4,5 |
| Crossing Point Variation   | $V_{XABSVAR}$ | Averaging off |      | 140  | mV    | 1,4,9 |
| Maximum Output Voltage     | $V_{HIGH}$    | Averaging off |      | 1150 | mV    | 1,7   |
| Minimum Output Voltage     | $V_{LOW}$     | Averaging off | -300 |      | mV    | 1,8   |
| Duty Cycle                 | $D_{CYC}$     | Averaging on  | 45   | 55   | %     | 2     |
| CPU Skew                   | $CPU_{SKEW}$  | Averaging on  |      | 100  | ps    |       |
| SRC Skew                   | $SRC_{SKEW}$  | Averaging on  |      | 3000 | ps    | 6     |

**NOTES on DIF Output AC Specs: (unless otherwise noted, guaranteed by design and characterization, not 100% tested in production).**

- <sup>1</sup>Measurement taken for single ended waveform on a component test board (not in system)
- <sup>2</sup>Measurement taken from differential waveform on a component test board. (not in system)
- <sup>3</sup>Slew rate emasured through  $V_{swing}$  voltage range centered about differential zero
- <sup>4</sup>Vcross is defined at the voltage where Clock = Clock#, measured on a component test board (not in system)
- <sup>5</sup>Only applies to the differential rising edge (Clock rising, Clock# falling)
- <sup>6</sup>Total distributed intentional SRC to SRC skew. PCIe Gen2 outputs (SRC3, 4, 6 and 7) will have 0 nominal skew. Maximum allowable interpair skew is 150 ps.
- <sup>7</sup>The max voltage including overshoot.
- <sup>8</sup>The min voltage including undershoot.
- <sup>9</sup>The total variation of all Vcross measurements in any particular system. Note this is a subset of  $V_{cross}$  min/mas ( $V_{Cross}$  absolute) allowed. The intent is to limit Vcross induced modulation by setting  $C_{cross\_delta}$  to be smaller than  $V_{Cross}$  absolute.
- <sup>10</sup>Matching applies to rising edge rate for Clock and falling edge rate for Clock#. It is measured using a +/-75mV window centered on the average cross point where Clock rising meets Clock# falling. The median cross point is used to calculate the voltage thresholds the oscilloscope is to use for the edge rate calculations.

**Clock Jitter Specs - Low Power Differential Outputs**

| PARAMETER                   | SYMBOL       | CONDITIONS               | MIN | MAX | UNITS | NOTES |
|-----------------------------|--------------|--------------------------|-----|-----|-------|-------|
| CPU Jitter - Cycle to Cycle | $CPUJ_{C2C}$ | Differential Measurement |     | 85  | ps    | 1     |
| SRC Jitter - Cycle to Cycle | $SRCJ_{G2C}$ | Differential Measurement |     | 125 | ps    | 1,2   |
| DOT Jitter - Cycle to Cycle | $DOTJ_{C2C}$ | Differential Measurement |     | 250 | ps    | 1     |


**NOTES on DIF Output Jitter: (unless otherwise noted, guaranteed by design and characterization, not 100% tested in production).**

- <sup>1</sup>Jitter specs are specified as measured on a clock characterization board. System designers need to take special care not to use these numbers, as the in-system performance will be somewhat degraded. The receiver EMTS (chispet or CPU) will have the receiver jitter specs as measured in a real system.
- <sup>2</sup>Phase jitter requirement: The designated Ge2 outputs will meet the reference clock jitter requirements from the PCI Express Gen2 Base Spec. The test is performed on a component test board under quiet conditions with all outputs on. Jitter analysis is performed using the standardized tool provided by the PCI SIG.

**Electrical Characteristics - PCICLK/PCICLK\_F**

| PARAMETER                    | SYMBOL                | CONDITIONS                             | MIN      | MAX      | UNITS | NOTES |
|------------------------------|-----------------------|----------------------------------------|----------|----------|-------|-------|
| Long Accuracy                | ppm                   | see T <sub>period</sub> min-max values | -100     | 100      | ppm   | 1,2   |
| Clock period                 | T <sub>period</sub>   | 33.33MHz output no spread              | 29.99700 | 30.00300 | ns    | 2     |
|                              |                       | 33.33MHz output spread                 | 30.08421 | 30.23459 | ns    | 2     |
| Absolute min/max period      | T <sub>abs</sub>      | 33.33MHz output no spread              | 29.49700 | 30.50300 | ns    | 2     |
|                              |                       | 33.33MHz output nominal/spread         | 29.56617 | 30.58421 | ns    | 2     |
| Rising Edge Slew Rate        | t <sub>SLR</sub>      | Measured from 0.8 to 2.0 V             | 1        | 4        | V/ns  | 1     |
| Falling Edge Slew Rate       | t <sub>FLR</sub>      | Measured from 2.0 to 0.8 V             | 1        | 4        | V/ns  | 1     |
| Pin to Pin Skew              | t <sub>skew</sub>     | V <sub>I</sub> = 1.5 V                 |          | 250      | ps    | 2     |
| Intentional PCI to PCI delay | t <sub>skew</sub>     | V <sub>I</sub> = 1.5 V                 | 100      | 200      | ps    | 2     |
| Duty Cycle                   | d <sub>11</sub>       | V <sub>I</sub> = 1.5 V                 | 45       | 55       | %     | 2     |
| Jitter, Cycle to cycle       | t <sub>1cyc-cyc</sub> | V <sub>I</sub> = 1.5 V                 |          | 500      | ps    | 2     |

**Intentional PCI Clock to Clock Delay**



**Electrical Characteristics - USB48MHz**

| PARAMETER               | SYMBOL                | CONDITIONS                             | MIN      | MAX      | UNITS | NOTES |
|-------------------------|-----------------------|----------------------------------------|----------|----------|-------|-------|
| Long Accuracy           | ppm                   | see T <sub>period</sub> min-max values | -100     | 100      | ppm   | 2,4   |
| Clock period            | T <sub>period</sub>   | 48.00MHz output nominal                | 20.83125 | 20.83542 | ns    | 2,3   |
| Absolute min/max period | T <sub>abs</sub>      | 48.00MHz output nominal                | 20.48125 | 21.18542 | ns    | 2     |
| CLK High Time           | T <sub>HIGH</sub>     |                                        | 8.216563 | 11.15198 | V     |       |
| CLK Low time            | T <sub>LOW</sub>      |                                        | 7.816563 | 10.95198 | V     |       |
| Rising Edge Slew Rate   | t <sub>SLR</sub>      | Measured from 0.8 to 2.0 V             | 1        | 2        | V/ns  | 1     |
| Falling Edge Slew Rate  | t <sub>FLR</sub>      | Measured from 2.0 to 0.8 V             | 1        | 2        | V/ns  | 1     |
| Duty Cycle              | d <sub>11</sub>       | V <sub>I</sub> = 1.5 V                 | 45       | 55       | %     | 2     |
| Jitter, Cycle to cycle  | t <sub>1cyc-cyc</sub> | V <sub>I</sub> = 1.5 V                 |          | 350      | ps    | 2     |

**Electrical Characteristics - REF-14.318MHz**

| PARAMETER               | SYMBOL                | CONDITIONS                             | MIN      | MAX      | UNITS | Notes |
|-------------------------|-----------------------|----------------------------------------|----------|----------|-------|-------|
| Long Accuracy           | ppm                   | see T <sub>period</sub> min-max values | -100     | 100      | ppm   | 2, 4  |
| Clock period            | T <sub>period</sub>   | 14.318MHz output nominal               | 69.82033 | 69.86224 | ns    | 2, 3  |
| Absolute min/max period | T <sub>abs</sub>      | 14.318MHz output nominal               | 69.83400 | 70.84800 | ns    | 2     |
| CLK High Time           | T <sub>HIGH</sub>     |                                        | 29.97543 | 38.46654 | V     |       |
| CLK Low time            | T <sub>LOW</sub>      |                                        | 29.57543 | 38.26654 | V     |       |
| Rising Edge Slew Rate   | t <sub>SLR</sub>      | Measured from 0.8 to 2.0 V             | 1        | 4        | V/ns  | 1     |
| Falling Edge Slew Rate  | t <sub>FLR</sub>      | Measured from 2.0 to 0.8 V             | 1        | 4        | V/ns  | 1     |
| Duty Cycle              | d <sub>11</sub>       | V <sub>I</sub> = 1.5 V                 | 45       | 55       | %     | 2     |
| Jitter, Cycle to cycle  | t <sub>1cyc-cyc</sub> | V <sub>I</sub> = 1.5 V                 |          | 1000     | ps    | 2     |

**NOTES on SE outputs: (unless otherwise noted, guaranteed by design and characterization, not 100% tested in production).**

<sup>1</sup>Edge rate in system is measured from 0.8V to 2.0V.

<sup>2</sup>Duty cycle, Period and Jitter are measured with respect to 1.5V

<sup>3</sup>The average period over any 1us period of time

<sup>4</sup>Using frequency counter with the measurement interval equal or greater that 0.15s, target frequencies are 14.318180 MHz, 33.333333MHz and 48.000000MHz

**Table 1: CPU Frequency Select Table**

| FS <sub>L</sub> C <sup>2</sup><br>B0b7 | FS <sub>L</sub> B <sup>1</sup><br>B0b6 | FS <sub>L</sub> A <sup>1</sup><br>B0b5 | CPU<br>MHz | SRC<br>MHz | PCI<br>MHz | REF<br>MHz | USB<br>MHz | DOT<br>MHz |
|----------------------------------------|----------------------------------------|----------------------------------------|------------|------------|------------|------------|------------|------------|
| 0                                      | 0                                      | 0                                      | 266.66     | 100.00     | 33.33      | 14.318     | 48.00      | 96.00      |
| 0                                      | 0                                      | 1                                      | 133.33     |            |            |            |            |            |
| 0                                      | 1                                      | 0                                      | 200.00     |            |            |            |            |            |
| 0                                      | 1                                      | 1                                      | 166.66     |            |            |            |            |            |
| 1                                      | 0                                      | 0                                      | 333.33     |            |            |            |            |            |
| 1                                      | 0                                      | 1                                      | 100.00     |            |            |            |            |            |
| 1                                      | 1                                      | 0                                      | 400.00     |            |            |            |            |            |
| 1                                      | 1                                      | 1                                      | Reserved   |            |            |            |            |            |

- FS<sub>L</sub>A and FS<sub>L</sub>B are low-threshold inputs. Please see V<sub>IL\_FS</sub> and V<sub>IH\_FS</sub> specifications in the Input/Supply/Common Output Parameters Table for correct values.  
Also refer to the Test Clarification Table.
- FS<sub>L</sub>C is a three-level input. Please see the V<sub>IL\_FS</sub> and V<sub>IH\_FS</sub> specifications in the Input/Supply/Common Output Parameters Table for correct values.

**Table 2: PLL3 Quick Configuration**

| B1b4 | B1b3 | B1b2 | B1b1 | Pin 17         | Pin 18      | Spread                          | Comment                            |
|------|------|------|------|----------------|-------------|---------------------------------|------------------------------------|
|      |      |      |      | MHz            | MHz         | %                               |                                    |
| 0    | 0    | 0    | 0    | PLL 3 disabled |             |                                 |                                    |
| 0    | 0    | 0    | 1    | 100.00         | 100.00      | 0.5% Down Spread                | SRCCLK1 from SRC_MAIN              |
| 0    | 0    | 1    | 0    | 100.00         | 100.00      | 0.5% Down Spread                | Only SRCCLK1 from PLL3             |
| 0    | 0    | 1    | 1    | 100.00         | 100.00      | 1% Down Spread                  | Only SRCCLK1 from PLL3             |
| 0    | 1    | 0    | 0    | 100.00         | 100.00      | 1.5% Down Spread                | Only SRCCLK1 from PLL3             |
| 0    | 1    | 0    | 1    | 100.00         | 100.00      | 2% Down Spread                  | Only SRCCLK1 from PLL3             |
| 0    | 1    | 1    | 0    | 100.00         | 100.00      | 2.5% Down Spread                | Only SRCCLK1 from PLL3             |
| 0    | 1    | 1    | 1    | N/A            | N/A         | N/A                             | N/A                                |
| 1    | 0    | 0    | 0    | 24.576         | 24.576      | None                            | 24.576Mhz on SE1 and SE2           |
| 1    | 0    | 0    | 1    | 24.576         | 98.304      | None                            | 24.576Mhz on SE1, 98.304Mhz on SE2 |
| 1    | 0    | 1    | 0    | 98.304         | 98.304      | None                            | 98.304Mhz on SE1 and SE2           |
| 1    | 0    | 1    | 1    | 27.000         | 27.000      | None                            | 27Mhz on SE1 and SE2               |
| 1    | 1    | 0    | 0    | 25.000         | 25.000      | None                            | 25Mhz on SE1 and SE2               |
| 1    | 1    | 0    | 1    | 27.00MHz       | 27.00MHz SS | 0.5% Down Spread<br>Pin 18 only | N/A                                |
| 1    | 1    | 1    | 0    | N/A            | N/A         | N/A                             | N/A                                |
| 1    | 1    | 1    | 1    | N/A            | N/A         | N/A                             | N/A                                |

**Table 3: IO\_Vout select table**

| B9b2 | B9b1 | B9b0 | IO_Vout |
|------|------|------|---------|
| 0    | 0    | 0    | 0.3V    |
| 0    | 0    | 1    | 0.4V    |
| 0    | 1    | 0    | 0.5V    |
| 0    | 1    | 1    | 0.6V    |
| 1    | 0    | 0    | 0.7V    |
| 1    | 0    | 1    | 0.8V    |
| 1    | 1    | 0    | 0.9V    |
| 1    | 1    | 1    | 1.0V    |

**Table 4: Device ID table**

| B8b7 | B8b6 | B8b5 | B8b4 | Comment      |
|------|------|------|------|--------------|
| 0    | 0    | 0    | 0    | 56 pin TSSOP |
| 0    | 0    | 0    | 1    | 64 pin TSSOP |
| 0    | 0    | 1    | 0    | Reserved     |
| 0    | 0    | 1    | 1    | Reserved     |
| 0    | 1    | 0    | 0    | Reserved     |
| 0    | 1    | 0    | 1    | Reserved     |
| 0    | 1    | 1    | 0    | Reserved     |
| 0    | 1    | 1    | 1    | Reserved     |
| 1    | 0    | 0    | 0    | Reserved     |
| 1    | 0    | 0    | 1    | Reserved     |
| 1    | 0    | 1    | 0    | Reserved     |
| 1    | 0    | 1    | 1    | Reserved     |
| 1    | 1    | 0    | 0    | Reserved     |
| 1    | 1    | 0    | 1    | Reserved     |
| 1    | 1    | 1    | 0    | Reserved     |
| 1    | 1    | 1    | 1    | Reserved     |

**CPU Power Management Table**

| PD#       | CPU_STOP# | PCI_STOP# | CR# | SMBus Register OE | CPU1    | CPU1#   | CPU(0,2) | CPU(0,2)# |
|-----------|-----------|-----------|-----|-------------------|---------|---------|----------|-----------|
| 1         | 1         | 1         | X   | Enable            | Running | Running | Running  | Running   |
| 0         | X         | X         | X   | Enable            | Low/20K | Low     | Low/20K  | Low       |
| 1         | 0         | X         | X   | Enable            | High    | Low     | High     | Low       |
| 1         | X         | X         | X   | Disable           | Low/20K | Low     | Low/20K  | Low       |
| <b>M1</b> |           |           |     |                   | Running | Running | Low/20K  | Low       |

**SRC, LCD, DOT Power Management Table**

| PD#       | CPU_STOP# | PCI_STOP# | CR# | SMBus Register OE | SRC/LCD  | SRC#/LCD# | SRC/LCD                   | SRC#/LCD# | DOT     | DOT#    |
|-----------|-----------|-----------|-----|-------------------|----------|-----------|---------------------------|-----------|---------|---------|
|           |           |           |     |                   | Free-Run |           | PCI Stoppable/CR Selected |           |         |         |
| 1         | X         | 1         | 0   | Enable            | Running  | Running   | Running                   | Running   | Running | Running |
| 0         | X         | X         | X   | Enable            | Low/20K  | Low       | Low/20K                   | Low       | Low/20K | Low     |
| 1         | X         | 0         | X   | Enable            | Running  | Running   | High                      | Low       | Running | Running |
| 1         | X         | X         | 1   | Enable            | Running  | Running   | Low/20K                   | Low       | Running | Running |
| 1         | X         | X         | X   | Disable           | Low/20K  | Low       | Low/20K                   | Low       | Low/20K | Low     |
| <b>M1</b> |           |           |     |                   | Low/20K  | Low       | Low/20K                   | Low       | Low/20K | Low     |

**Singled-ended Power Management Table**

| PD#       | CPU_STOP# | PCI_STOP# | CR# | SMBus Register OE | PCIF/PCI | PCIF/PCI  | USB     | REF     |
|-----------|-----------|-----------|-----|-------------------|----------|-----------|---------|---------|
|           |           |           |     |                   | Free-run | Stoppable |         |         |
| 1         | X         | 1         | X   | Enable            | Running  | Running   | Running | Running |
| 0         | X         | X         | X   | Enable            | Low      | Low       | Low     | Low     |
| 1         | X         | 0         | X   | Enable            | Running  | Low       | Running | Running |
| 1         | X         | X         | X   | Disable           | Low      | Low       | Low     | Low     |
| <b>M1</b> |           |           |     |                   | Low      | Low       | Low     | Low     |

## General SMBus serial interface information for the ICS9LP505-1

### How to Write:

- Controller (host) sends a start bit.
- Controller (host) sends the write address D2<sub>(h)</sub>
- ICS clock will **acknowledge**
- Controller (host) sends the beginning byte location = N
- ICS clock will **acknowledge**
- Controller (host) sends the data byte count = X
- ICS clock will **acknowledge**
- Controller (host) starts sending **Byte N through Byte N + X - 1**
- ICS clock will **acknowledge** each byte **one at a time**
- Controller (host) sends a Stop bit

### How to Read:

- Controller (host) will send start bit.
- Controller (host) sends the write address D2<sub>(h)</sub>
- ICS clock will **acknowledge**
- Controller (host) sends the beginning byte location = N
- ICS clock will **acknowledge**
- Controller (host) will send a separate start bit.
- Controller (host) sends the read address D3<sub>(h)</sub>
- ICS clock will **acknowledge**
- ICS clock will send the data byte count = X
- ICS clock sends **Byte N + X - 1**
- ICS clock sends **Byte 0 through byte X (if X<sub>(h)</sub> was written to byte 8).**
- Controller (host) will need to acknowledge each byte
- Controller (host) will send a not acknowledge bit
- Controller (host) will send a stop bit

| Index Block Write Operation     |           |                      |
|---------------------------------|-----------|----------------------|
| Controller (Host)               |           | ICS (Slave/Receiver) |
| T                               | starT bit |                      |
| Slave Address D2 <sub>(h)</sub> |           |                      |
| WR                              | WRite     |                      |
|                                 |           | ACK                  |
| Beginning Byte = N              |           |                      |
|                                 |           | ACK                  |
| Data Byte Count = X             |           |                      |
|                                 |           | ACK                  |
| Beginning Byte N                | X Byte    |                      |
| ○                               |           | ACK                  |
| ○                               |           | ○                    |
| ○                               |           | ○                    |
| Byte N + X - 1                  |           | ○                    |
|                                 |           | ACK                  |
| P                               | stoP bit  |                      |

| Index Block Read Operation      |                 |                      |
|---------------------------------|-----------------|----------------------|
| Controller (Host)               |                 | ICS (Slave/Receiver) |
| T                               | starT bit       |                      |
| Slave Address D2 <sub>(h)</sub> |                 |                      |
| WR                              | WRite           |                      |
|                                 |                 | ACK                  |
| Beginning Byte = N              |                 |                      |
|                                 |                 | ACK                  |
| RT                              | Repeat starT    |                      |
| Slave Address D3 <sub>(h)</sub> |                 |                      |
| RD                              | ReaD            |                      |
|                                 |                 | ACK                  |
|                                 |                 | Data Byte Count = X  |
| ACK                             |                 |                      |
| ACK                             |                 | Beginning Byte N     |
| ○                               |                 | ○                    |
| ○                               |                 | ○                    |
| ○                               |                 | ○                    |
|                                 |                 | Byte N + X - 1       |
| N                               | Not acknowledge |                      |
| P                               | stoP bit        |                      |

**Byte 0 FS Readback and PLL Selection Register**

| Bit | Pin | Name         | Description                                                                                                                                                                                                        | Type | 0                                        | 1                   | Default |
|-----|-----|--------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------|------------------------------------------|---------------------|---------|
| 7   | -   | FSLC         | CPU Freq. Sel. Bit (Most Significant)                                                                                                                                                                              | R    | See Table 1 : CPU Frequency Select Table |                     | Latch   |
| 6   | -   | FSLB         | CPU Freq. Sel. Bit                                                                                                                                                                                                 | R    |                                          |                     | Latch   |
| 5   | -   | FSLA         | CPU Freq. Sel. Bit (Least Significant)                                                                                                                                                                             | R    |                                          |                     | Latch   |
| 4   | -   | iAMT_EN      | Set via SMBus or dynamically by CK505 if detects dynamic M1                                                                                                                                                        | RW   | Legacy Mode                              | iAMT Enabled        | 0       |
| 3   |     | Reserved     | Reserved                                                                                                                                                                                                           | RW   |                                          |                     | 0       |
| 2   | -   | SRC_Main_SEL | Select source for SRC Main                                                                                                                                                                                         | RW   | SRC Main = PLL1                          | SRC Main = PLL3     | 0       |
| 1   | -   | SATA_SEL     | Select source for SATA clock                                                                                                                                                                                       | RW   | SATA = SRC_Main                          | SATA = PLL2         | 0       |
| 0   | -   | PD_Restore   | 1 = on Power Down de-assert return to last known state<br>0 = clear all SMBus configurations as if cold power-on and go to latches open state<br>This bit is ignored and treated as '1' if device is in iAMT mode. | RW   | Configuration Not Saved                  | Configuration Saved | 1       |

**Byte 1 DOT96 Select and PLL3 Quick Config Register**

| Bit | Pin   | Name         | Description                    | Type | 0                                                                                  | 1             | Default |
|-----|-------|--------------|--------------------------------|------|------------------------------------------------------------------------------------|---------------|---------|
| 7   | 13/14 | SRC0_SEL     | Select SRC0 or DOT96           | RW   | SRC0                                                                               | DOT96         | 0       |
| 6   | -     | PLL1_SSC_SEL | Select 0.5% down or center SSC | RW   | Down spread                                                                        | Center spread | 0       |
| 5   |       | PLL3_SSC_SEL | Select 0.5% down or center SSC | RW   | Down spread                                                                        | Center spread | 0       |
| 4   |       | PLL3_CF3     | PLL3 Quick Config Bit 3        | RW   | See Table 2: PLL3 Quick Configuration<br><b>Only applies if Byte 0, bit 2 = 0.</b> |               | 0       |
| 3   |       | PLL3_CF2     | PLL3 Quick Config Bit 2        | RW   |                                                                                    |               | 0       |
| 2   |       | PLL3_CF1     | PLL3 Quick Config Bit 1        | RW   |                                                                                    |               | 0       |
| 1   |       | PLL3_CF0     | PLL3 Quick Config Bit 0        | RW   |                                                                                    |               | 1       |
| 0   |       | PCI_SEL      | PCI_SEL                        | RW   | PCI from PLL1                                                                      | PCI from      | 1       |

**Byte 2 Output Enable Register**

| Bit | Pin | Name    | Description                                             | Type | 0               | 1              | Default |
|-----|-----|---------|---------------------------------------------------------|------|-----------------|----------------|---------|
| 7   |     | REF_OE  | Output enable for REF, if disabled output is tri-stated | RW   | Output Disabled | Output Enabled | 1       |
| 6   |     | USB_OE  | Output enable for USB                                   | RW   | Output Disabled | Output Enabled | 1       |
| 5   |     | PCI5_OE | Output enable for PCI5                                  | RW   | Output Disabled | Output Enabled | 1       |
| 4   |     | PCI4_OE | Output enable for PCI4                                  | RW   | Output Disabled | Output Enabled | 1       |
| 3   |     | PCI3_OE | Output enable for PCI3                                  | RW   | Output Disabled | Output Enabled | 1       |
| 2   |     | PCI2_OE | Output enable for PCI2                                  | RW   | Output Disabled | Output Enabled | 1       |
| 1   |     | PCI1_OE | Output enable for PCI1                                  | RW   | Output Disabled | Output Enabled | 1       |
| 0   |     | PCI0_OE | Output enable for PCI0                                  | RW   | Output Disabled | Output Enabled | 1       |

**Byte 3 Output Enable Register**

| Bit | Pin | Name        | Description                   | Type | 0               | 1              | Default |
|-----|-----|-------------|-------------------------------|------|-----------------|----------------|---------|
| 7   |     | SRC11_OE    | Output enable for SRC11       | RW   | Output Disabled | Output Enabled | 1       |
| 6   |     | SRC10_OE    | Output enable for SRC10       | RW   | Output Disabled | Output Enabled | 1       |
| 5   |     | SRC9_OE     | Output enable for SRC9        | RW   | Output Disabled | Output Enabled | 1       |
| 4   |     | SRC8/ITP_OE | Output enable for SRC8 or ITP | RW   | Output Disabled | Output Enabled | 1       |
| 3   |     | SRC7_OE     | Output enable for SRC7        | RW   | Output Disabled | Output Enabled | 1       |
| 2   |     | SRC6_OE     | Output enable for SRC6        | RW   | Output Disabled | Output Enabled | 1       |
| 1   |     | SRC5_OE     | Output enable for SRC5        | RW   | Output Disabled | Output Enabled | 1       |
| 0   |     | SRC4_OE     | Output enable for SRC4        | RW   | Output Disabled | Output Enabled | 1       |

**Byte 4 Output Enable and Spread Spectrum Disable Register**

| Bit | Pin | Name          | Description                     | Type | 0               | 1              | Default |
|-----|-----|---------------|---------------------------------|------|-----------------|----------------|---------|
| 7   |     | SRC3_OE       | Output enable for SRC3          | RW   | Output Disabled | Output Enabled | 1       |
| 6   |     | SATA/SRC2_OE  | Output enable for SATA/SRC2     | RW   | Output Disabled | Output Enabled | 1       |
| 5   |     | SRC1_OE       | Output enable for SRC1          | RW   | Output Disabled | Output Enabled | 1       |
| 4   |     | SRC0/DOT96_OE | Output enable for SRC0/DOT96    | RW   | Output Disabled | Output Enabled | 1       |
| 3   |     | CPU1_OE       | Output enable for CPU1          | RW   | Output Disabled | Output Enabled | 1       |
| 2   |     | CPU0_OE       | Output enable for CPU0          | RW   | Output Disabled | Output Enabled | 1       |
| 1   |     | PLL1_SSC_ON   | Enable PLL1's spread modulation | RW   | Spread Disabled | Spread Enabled | 1       |
| 0   |     | PLL3_SSC_ON   | Enable PLL3's spread modulation | RW   | Spread Disabled | Spread Enabled | 1       |

**Byte 5 Clock Request Enable/Configuration Register**

| Bit | Pin | Name      | Description                                                                | Type | 0             | 1             | Default |
|-----|-----|-----------|----------------------------------------------------------------------------|------|---------------|---------------|---------|
| 7   |     | CR#_A_EN  | Enable CR#_A (clk req),<br>PCI0_OE must be = 1 for this bit to take effect | RW   | Disable CR#_A | Enable CR#_A  | 0       |
| 6   |     | CR#_A_SEL | Sets CR#_A to control either SRC0 or SRC2                                  | RW   | CR#_A -> SRC0 | CR#_A -> SRC2 | 0       |
| 5   |     | CR#_B_EN  | Enable CR#_B (clk req)                                                     | RW   | Disable CR#_B | Enable CR#_B  | 0       |
| 4   |     | CR#_B_SEL | Sets CR#_B -> SRC1 or SRC4                                                 | RW   | CR#_B -> SRC1 | CR#_B -> SRC4 | 0       |
| 3   |     | CR#_C_EN  | Enable CR#_C (clk req)                                                     | RW   | Disable CR#_C | Enable CR#_C  | 0       |
| 2   |     | CR#_C_SEL | Sets CR#_C -> SRC0 or SRC2                                                 | RW   | CR#_C -> SRC0 | CR#_C -> SRC2 | 0       |
| 1   |     | CR#_D_EN  | Enable CR#_D (clk req)                                                     | RW   | Disable CR#_D | Enable CR#_D  | 0       |
| 0   |     | CR#_D_SEL | Sets CR#_D -> SRC1 or SRC4                                                 | RW   | CR#_D -> SRC1 | CR#_D -> SRC4 | 0       |

**Byte 6 Clock Request Enable/Configuration and Stop Control Register**

| Bit | Pin | Name                    | Description                                    | Type | 0             | 1                       | Default |
|-----|-----|-------------------------|------------------------------------------------|------|---------------|-------------------------|---------|
| 7   |     | CR#_E_EN                | Enable CR#_E (clk req) -> SRC6                 | RW   | Disable CR#_E | Enable CR#_E            | 0       |
| 6   |     | CR#_F_EN                | Enable CR#_F (clk req) -> SRC8                 | RW   | Disable CR#_F | Enable CR#_F            | 0       |
| 5   |     | CR#_G_EN                | Enable CR#_G (clk req) -> SRC9                 | RW   | Disable CR#_G | Enable CR#_G            | 0       |
| 4   |     | CR#_H_EN                | Enable CR#_H (clk req) -> SRC10                | RW   | Disable CR#_H | Enable CR#_H            | 0       |
| 3   |     | Reserved                | Reserved                                       | RW   |               |                         | 0       |
| 2   |     | Reserved                | Reserved                                       | RW   |               |                         | 0       |
| 1   |     | SSCD_STP_CRTL<br>(SRC1) | If set, SSCD (SRC1) stops with PCI_STOP#       | RW   | Free Running  | Stops with<br>PCI_STOP# | 0       |
| 0   |     | SRC_STP_CRTL            | If set, SRCs (except SRC1) stop with PCI_STOP# | RW   | Free Running  | Stops with              | 0       |

**Byte 7 Vendor ID/ Revision ID**

| Bit | Pin | Name            | Description                      | Type | 0               | 1 | Default |
|-----|-----|-----------------|----------------------------------|------|-----------------|---|---------|
| 7   |     | Rev Code Bit 3  | Revision ID                      | R    | Vendor specific |   | X       |
| 6   |     | Rev Code Bit 2  |                                  | R    |                 |   | X       |
| 5   |     | Rev Code Bit 1  |                                  | R    |                 |   | X       |
| 4   |     | Rev Code Bit 0  |                                  | R    |                 |   | X       |
| 3   |     | Vendor ID bit 3 | Vendor ID<br>ICS is 0001, binary | R    |                 |   | 0       |
| 2   |     | Vendor ID bit 2 |                                  | R    |                 |   | 0       |
| 1   |     | Vendor ID bit 1 |                                  | R    |                 |   | 0       |
| 0   |     | Vendor ID bit 0 |                                  | R    | 1               |   |         |

**Byte 8 Device ID and Output Enable Register**

| Bit | Pin | Name       | Description                                                                                       | Type | 0                   | 1       | Default |
|-----|-----|------------|---------------------------------------------------------------------------------------------------|------|---------------------|---------|---------|
| 7   |     | Device ID3 | Table of Device identifier codes, used for<br>differentiating between CK505 package options, etc. | R    | See Device ID Table |         | 0       |
| 6   |     | Device ID2 |                                                                                                   | R    |                     |         | 0       |
| 5   |     | Device ID1 |                                                                                                   | R    |                     |         | 0       |
| 4   |     | Device ID0 |                                                                                                   | R    |                     |         | 1       |
| 3   |     | Reserved   | Reserved                                                                                          | RW   | -                   | -       | 0       |
| 2   |     | Reserved   | Reserved                                                                                          | RW   | -                   | -       | 0       |
| 1   |     | SE1_OE     | Output enable for SE1                                                                             | RW   | Disabled            | Enabled | 0       |
| 0   |     | SE2_OE     | Output enable for SE2                                                                             | RW   | Disabled            | Enabled | 0       |

**Byte 9 Output Control Register**

| Bit | Pin | Name             | Description                                         | Type | 0                                                | 1               | Default |
|-----|-----|------------------|-----------------------------------------------------|------|--------------------------------------------------|-----------------|---------|
| 7   |     | PCIF5_STOP_EN    | Allows control of PCIF5 with assertion of PCI_STOP# | RW   | Free running                                     | Stops with      | 0       |
| 6   |     | TME_Readback     | Trusted Mode Enable (TME) strap status              | R    | normal operation                                 | no overclocking | 0       |
| 5   |     | REF_Strength     | Sets the REF output drive strength                  | RW   | 1X (2Loads)                                      | 2X (3 Loads)    | 1       |
| 4   |     | Test Mode Select | Allows test select, ignores REF/FSC/TestSel         | RW   | Outputs HI-Z                                     | Outputs = REF/N | 0       |
| 3   |     | Test Mode Entry  | Allows entry into test mode, ignores FSB/TestMode   | RW   | Normal operation                                 | Test mode       | 0       |
| 2   |     | IO_VOUT2         | IO Output Voltage Select (Most Significant Bit)     | RW   | See Table 3: V_IO Selection<br>(Default is 0.8V) |                 | 1       |
| 1   |     | IO_VOUT1         | IO Output Voltage Select                            | RW   |                                                  |                 | 0       |
| 0   |     | IO_VOUT0         | IO Output Voltage Select (Least Significant Bit)    | RW   |                                                  |                 | 1       |



**Byte 10 CK505 Rev 0.85 functions (ICS Rev H silicon and higher)**

| Bit | Pin | Name              | Description                             | Type | 0            | 1            | Default |
|-----|-----|-------------------|-----------------------------------------|------|--------------|--------------|---------|
| 7   |     | SRC5_EN Readback  | Readback of SRC5 enable latch           | R    | CPU/PCI Stop | SRC5 Enabled | Latch   |
| 6   |     | Reserved          | Reserved                                | RW   | -            | -            | 0       |
| 5   |     | Reserved          |                                         | RW   | -            | -            | 0       |
| 4   |     | Reserved          |                                         | RW   | -            | -            | 0       |
| 3   |     | Reserved          |                                         | RW   | -            | -            | 0       |
| 2   |     | Reserved          |                                         | RW   | -            | -            | 0       |
| 1   |     | CPU 1 Stop Enable | Enables control of CPU1 with CPU_STOP#  | RW   | Free Running | Stoppable    | 1       |
| 0   |     | CPU 0 Stop Enable | Enables control of CPU 0 with CPU_STOP# | RW   | Free Running | Stoppable    | 1       |

**Byte 11 Reserved Register**

| Bit | Pin | Name     | Description | Type | 0 | 1 | Default |
|-----|-----|----------|-------------|------|---|---|---------|
| 7   |     | Reserved | Reserved    | RW   | - | - | 0       |
| 6   |     | Reserved |             | RW   | - | - | 0       |
| 5   |     | Reserved |             | RW   | - | - | 0       |
| 4   |     | Reserved |             | RW   | - | - | 0       |
| 3   |     | Reserved |             | RW   | - | - | 0       |
| 2   |     | Reserved |             | RW   | - | - | 0       |
| 1   |     | Reserved |             | RW   | - | - | 0       |
| 0   |     | Reserved |             | RW   | - | - | 0       |

**Byte 12 Byte Count Register**

| Bit | Pin | Name     | Description                                      | Type | 0 | 1 | Default |
|-----|-----|----------|--------------------------------------------------|------|---|---|---------|
| 7   |     | Reserved | Read Back byte count register,<br>max bytes = 32 | RW   | - | - | 0       |
| 6   |     | Reserved |                                                  | RW   | - | - | 0       |
| 5   |     | BC5      |                                                  | RW   |   |   | 0       |
| 4   |     | BC4      |                                                  | RW   |   |   | 0       |
| 3   |     | BC3      |                                                  | RW   |   |   | 1       |
| 2   |     | BC2      |                                                  | RW   |   |   | 1       |
| 1   |     | BC1      |                                                  | RW   |   |   | 0       |
| 0   |     | BC0      |                                                  | RW   |   |   | 1       |


\*Accessing any SMBus bytes not shown in the datasheet could result in incorrect clock functions

### Test Clarification Table

| Comments                                                                           | HW                          |                                  | SW                        |                          | OUTPUT |
|------------------------------------------------------------------------------------|-----------------------------|----------------------------------|---------------------------|--------------------------|--------|
|                                                                                    | FSLC/<br>TEST_SEL<br>HW PIN | FSLB/<br>TEST_MOD<br>E<br>HW PIN | TEST<br>ENTRY BIT<br>B9b3 | REF/N or<br>HI-Z<br>B9b4 |        |
|                                                                                    | <2.0V                       | X                                | 0                         | 0                        | NORMAL |
| Power-up w/ TEST_SEL = 1 to enter test mode                                        | >2.0V                       | 0                                | X                         | 0                        | HI-Z   |
| Cycle power to disable test mode                                                   | >2.0V                       | 0                                | X                         | 1                        | REF/N  |
| FSLC./TEST_SEL -->3-level latched input                                            | >2.0V                       | 1                                | X                         | 0                        | REF/N  |
| If power-up w/ V>2.0V then use TEST_SEL                                            |                             |                                  |                           |                          |        |
| If power-up w/ V<2.0V then use FSLC                                                | >2.0V                       | 1                                | X                         | 1                        | REF/N  |
| FSLB/TEST_MODE -->low Vth input                                                    |                             |                                  |                           |                          |        |
| TEST_MODE is a real time input                                                     |                             |                                  |                           |                          |        |
|                                                                                    | <2.0V                       | X                                | 1                         | 0                        | HI-Z   |
| If TEST_SEL HW pin is 0 during power-up,<br>test mode can be invoked through B9b3. |                             |                                  |                           |                          |        |
| If test mode is invoked by B9b3, only B9b4<br>is used to select HI-Z or REF/N      | <2.0V                       | X                                | 1                         | 1                        | REF/N  |
| FSLB/TEST_Mode pin is not used.                                                    |                             |                                  |                           |                          |        |
| Cycle power to disable test mode, one shot control                                 |                             |                                  |                           |                          |        |

B9b3: 1= ENTER TEST MODE, Default = 0 (NORMAL OPERATION)

B9b4: 1= REF/N, Default = 0 (HI-Z)



6.10 mm. Body, 0.50 mm. Pitch TSSOP  
(240 mil) (20 mil)

| SYMBOL | In Millimeters<br>COMMON DIMENSIONS |      | In Inches<br>COMMON DIMENSIONS |      |
|--------|-------------------------------------|------|--------------------------------|------|
|        | MIN                                 | MAX  | MIN                            | MAX  |
| A      | --                                  | 1.20 | --                             | .047 |
| A1     | 0.05                                | 0.15 | .002                           | .006 |
| A2     | 0.80                                | 1.05 | .032                           | .041 |
| b      | 0.17                                | 0.27 | .007                           | .011 |
| c      | 0.09                                | 0.20 | .0035                          | .008 |
| D      | SEE VARIATIONS                      |      | SEE VARIATIONS                 |      |
| E      | 8.10 BASIC                          |      | 0.319 BASIC                    |      |
| E1     | 6.00                                | 6.20 | .236                           | .244 |
| e      | 0.50 BASIC                          |      | 0.020 BASIC                    |      |
| L      | 0.45                                | 0.75 | .018                           | .030 |
| N      | SEE VARIATIONS                      |      | SEE VARIATIONS                 |      |
| α      | 0°                                  | 8°   | 0°                             | 8°   |
| aaa    | --                                  | 0.10 | --                             | .004 |

VARIATIONS

| N  | D mm. |       | D (inch) |      |
|----|-------|-------|----------|------|
|    | MIN   | MAX   | MIN      | MAX  |
| 64 | 16.90 | 17.10 | .665     | .673 |

Reference Doc.: JEDEC Publication 95, MO-153


10-0039

## Ordering Information

9LP505-1yGLFT

Example:

XXXX y G LFT



### Revision History

| Rev. | Issue Date | Description                         | Page # |
|------|------------|-------------------------------------|--------|
| A    | 1/19/2007  | Updated IDD to CK505 Rev 1.0 specs  | -      |
| B    | 8/29/2007  | Removed SSOP Package Information.   | -      |
| C    | 11/2/2007  | Added Foot note to SMBus.           | 18     |
| D    | 4/1/2008   | Updated Electrical Characteristics. | 8-10   |
| E    | 12/17/2008 | Added Tcase spec.                   | 8      |
| F    | 2/27/2009  | Removed CFG0 reference.             | 8      |

## IMPORTANT NOTICE AND DISCLAIMER

RENESAS ELECTRONICS CORPORATION AND ITS SUBSIDIARIES (“RENESAS”) PROVIDES TECHNICAL SPECIFICATIONS AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF THIRD-PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for developers who are designing with Renesas products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. Renesas grants you permission to use these resources only to develop an application that uses Renesas products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Renesas intellectual property or to any third-party intellectual property. Renesas disclaims responsibility for, and you will fully indemnify Renesas and its representatives against, any claims, damages, costs, losses, or liabilities arising from your use of these resources. Renesas' products are provided only subject to Renesas' Terms and Conditions of Sale or other applicable terms agreed to in writing. No use of any Renesas resources expands or otherwise alters any applicable warranties or warranty disclaimers for these products.

(Disclaimer Rev.1.01 Jan 2024)

### Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,  
Koto-ku, Tokyo 135-0061, Japan  
[www.renesas.com](http://www.renesas.com)

### Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

### Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit [www.renesas.com/contact-us/](http://www.renesas.com/contact-us/).

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Renesas Electronics:](#)

[9LP505-1HGLF](#) [9LP505-1HGLFT](#)