



Secure KVM Switch, DVI to DVI/VGA - 4-Port, NIAP EAL2+ Certified, Audio, CAC Support, Single Monitor

MODEL NUMBER: B002-DUA4







Safely switch between up to 4 computers with different levels of security. This NIAP-certified KVM Switch offers superior security and data protection for government / military agencies that require absolutely secure networks - read Government Computer

Description

The Tripp Lite B002-DUA4 4 Port DVI / USB Secure KVM Switch with Audio offers secure and reliable access for any government/military desktop environment where security is required, by providing safe switching between computers operating on different networks. NIAP-certified to comply with Common Criteria EAL2+ security requirements

Hardware security includes: tamper-evident tape, chassis intrusion detection, and tamper-proof hardware, while software security includes restricted USB connectivity — non HIDs (Human Interface Devices) are ignored when switching — an isolated channel per port that makes it impossible for data to be transferred between secure and unsecured computers, and automatic clearing of the keyboard buffer. CAC (Common Access Card) support*

By combining physical security with controlled USB connectivity, the B002-DUA4 gives you the means to consolidate multiple workstations of various security classification levels with one keyboard, monitor and mouse (KVM) console.

* CAC support not validated by NIAP

Features

- National Information Assurance Partnership (NIAP) certified to comply with Common Criteria EAL2+ security requirements
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases.
- · Safely switch between computers with varying security levels.
- Isolated Channels Each port is its own channel, making it impossible for data to be transferred between connected computers.
- Tamper-Warning Labels Tamper-Warning labels will be placed on each side of the KVM, providing visual evidence if the unit has been tampered with or compromised.
- Housing Intrusion Protection Technology Housing Intrusion Protection technology disables the KVM if the housing is opened, causing it to become inoperable. When disabled, the front panel LEDs will flash repeatedly.
- Tamper-Proof Components All internal circuitry is soldered directly to the board, preventing the components from being tampered with.

Highlights

- 4-Port NIAP-Certified Secure DVI / USB KVM Switch with Audio
- Tested to comply with Common Criteria EAL2+ security requirements
- Multi-platform support: Windows, Linux, MAC, and SUN
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases
- CAC Support*

System Requirements

- DVI or VGA Monitor
- USB Mouse and Keyboard
- Computer with DVI or VGA port
- Computer with USB Port
- Microphone with 3.5mm Male connector (optional)
- Speakers with 3.5mm Male connector (optional)
- Compatible with all major operating systems

Package Includes

- B002-DUA4 4-Port Secure KVM Switch
- C13 5-15P Power Cord
- (4) Foot Pads
- Owner's Manual



- Fixed Firmware Firmware is non-reprogrammable, securing against attempts to alter the logic of the KVM.
- Automatic Keyboard Buffer Clearing The keyboard buffer is automatically cleared after data transmission, leaving no information stored in the switch.
- No Memory Buffer The only way to access connected computers is via push button. Port switching
 methods such as On-Screen Display (OSD) and Hot key Commands, which require memory, have been
 excluded to further ensure data integrity.
- Compatible with all major operating systems: Windows, Linux, MAC, and SUN
- DVI-I Dual-Link signal supports digital video resolutions up to 2560 x 1600, and analog video resolutions up to 2048 x 1536.
- Supports transfer of EDID information, allowing for optimal display performance.
- Audio support for both speaker and microphone.
- CAC Support (CAC support not validated by NIAP)

Specifications

PC Code 037332167682 fax CPU 4 fax CPU DVI; Stereo Audio NPUT 100V AC; 110V AC; 115V AC; 120V AC; 120V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC kominal Input Voltage (s) Supported 100V AC; 110V AC; 115V AC; 120V AC; 120V AC; 120V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC kominal Input Voltage Description 100-240V, 50/60 Hz, 0.5A nput Frequency 50/60Hz nput Current 120V (0.4A) / 230V (0.2A) Power Consumption (Watts) 5.1 5.1W (120V), 5.1W (230V) Consumption Detail 5.1W (120V), 5.1W (230V) Consumption Detail 4 Computer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x DVI-1, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Corputer/Server Ports 4 x 3.5mm (Speaker / Microphone)		
Aax CPU 4 Aax CPU 4 iechnology DVI; Stereo Audio NPUT Adminal Input Voltage(s) Supported 100V AC; 110V AC; 115V AC; 120V AC; 127V AC; 140V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC Adminal Input Voltage Description 100-240V, 50/60 Hz, 0.5A Anput Frequency 50/60Hz Anput Current 120V (0.4A) / 230V (0.2A) POWER 5.1 Prover Consumption (Watts) 5.1 Stower Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 4 POWER 4 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 4 POWER 5.1 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 4 POWER 4 POWER 5.1 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 5.1 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 4 POWER 4 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 5.1 Prover Consumption Detail 5.1/W (120V), 5.1W (230V) POWER 4 POWER	OVERVIEW	
Point DVI; Stereo Audio NPUT DVI Atominal Input Voltage(s) Supported 100V AC; 115V AC; 120V AC; 127V AC; 140V AC; 200V AC; 220V AC; 230V AC; 240V AC Atominal Input Voltage Description 100-240V, 50/60 Hz, 0.5A Nput Frequency 50/60Hz apput Current 120V (0.4A) / 230V (0.2A) POWER 5.1 Power Consumption (Watts) 5.1 5.1W (120V), 5.1W (230V) 5.1W Power Consumption Detail 5.1W (120V), 5.1W (230V) POWER Consumption Detail 5.1 Prover Consumption Detail 5.1W (120V), 5.1W (230V) POWER Consumption Detail 5.1W (120V), 5.1W (230V) Prover Consumption Detail 5.1W (120V), 5.1W (230V) Prover Consumption Detail 5.1W (120V), 5.1W (230V) Prover Consumption Detail 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) Prover Console Ports 4 x SDV-I, 1 & x USB "B", 8 x 3.5mm (Speaker/Microphone) Prover Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone) Prover Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone) Prover Console Ports - Port 4 2 x 3.5mm (Speak	UPC Code	037332167682
NPUT Atominal Input Voltage(s) Supported 100V AC; 110V AC; 115V AC; 120V AC; 127V AC; 140V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC Atominal Input Voltage Description 100-240V, 50/60 Hz, 0.5A Anput Frequency 50/60Hz Apput Current 120V (0.4A) / 230V (0.2A) Power 5.1 Power Consumption (Watts) 5.1 Power Consumption Detail 5.1W (120V), 5.1W (230V) Power Consumption Detail 5.1W (120V), 5.1W (230V) Power Consumption Potal 5.1W (120V), 5.1W (230V) Power Consumption Detail 5.1W (120V), 5.1W (230V) Power Console Ports 4 Power Console Ports 4 x DVH, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone)	Max CPU	4
Aominal Input Voltage(s) Supported 100V AC; 110V AC; 115V AC; 120V AC; 127V AC; 140V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC Aominal Input Voltage Description 100-240V, 50/60 Hz, 0.5A Apput Frequency 50/60Hz Apput Frequency 50/60Hz Apput Current 120V (0.4A) / 230V (0.2A) Power Consumption (Watts) 5.1 Power Consumption Detail 5.1W (120V), 5.1W (230V) CONNECTIONS 4 Aumber of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Accal Console Ports - Port 3 USB - Keyboard Accal Console Ports - Port 4 2 x 3.5mm (Speaker/Microphone)	Technology	DVI; Stereo Audio
Induction 100-240V, 50/60 Hz, 0.5A Input Frequency 50/60 Hz Input Current 120V (0.4A) / 230V (0.2A) POWER Power Consumption (Watts) 5.1 5.1 Power Consumption Detail 5.1 W (120V), 5.1W (230V) POWER POWER Power Consumption (Watts) 5.1 5.1 W (120V), 5.1W (230V) POWER POWER POWER POWER Power Consumption (Watts) 5.1 5.1 W (120V), 5.1W (230V) POWER POWER <	INPUT	
by the product of t	Nominal Input Voltage(s) Supported	100V AC; 110V AC; 115V AC; 120V AC; 127V AC; 140V AC; 200V AC; 208V AC; 220V AC; 230V AC; 240V AC
nput Current 120V (0.4A) / 230V (0.2A) Power 5.1 Power Consumption (Watts) 5.1 Power Consumption Detail 5.1W (120V), 5.1W (230V) CONNECTIONS 4 Number of Ports 4 A x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB ocal Console Ports - Port 3 USB - Keyboard ocal Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Nominal Input Voltage Description	100-240V, 50/60 Hz, 0.5A
POWER Power Consumption (Watts) 5.1 Power Consumption Detail 5.1W (120V), 5.1W (230V) CONNECTIONS Jumber of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Input Frequency	50/60Hz
Power Consumption (Watts) 5.1 Power Consumption Detail 5.1W (120V), 5.1W (230V) CONNECTIONS 4 Number of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Input Current	120V (0.4A) / 230V (0.2A)
Power Consumption Detail 5.1W (120V), 5.1W (230V) CONNECTIONS Jumber of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	POWER	
CONNECTIONS Number of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Power Consumption (Watts)	5.1
Aumber of Ports 4 Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Power Consumption Detail	5.1W (120V), 5.1W (230V)
Computer/Server Ports 4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone) PC/Server Connections DVI; USB cocal Console Ports - Port 3 USB - Keyboard cocal Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	CONNECTIONS	
PC/Server Connections DVI; USB .ocal Console Ports - Port 3 USB - Keyboard .ocal Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Number of Ports	4
Local Console Ports - Port 3 USB - Keyboard Local Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone)	Computer/Server Ports	4 x DVI-I, 4 x USB "B", 8 x 3.5mm (Speaker/Microphone)
Accal Console Ports - Port 4 2 x 3.5mm (Speaker / Microphone) PHYSICAL Color Black	PC/Server Connections	DVI; USB
PHYSICAL Color Black	Local Console Ports - Port 3	USB - Keyboard
Color Black	Local Console Ports - Port 4	2 x 3.5mm (Speaker / Microphone)
	PHYSICAL	
Shipping Dimensions (hwd / in.) 4.60 x 16.30 x 8.50	Color	Black
	Shipping Dimensions (hwd / in.)	4.60 x 16.30 x 8.50





Shipping Dimensions (hwd / cm)	11.68 x 41.40 x 21.59
Shipping Weight (lbs.)	5.70
Shipping Weight (kg)	2.59
Unit Dimensions (hwd / in.)	1.750 x 13.200 x 6.100
Unit Dimensions (hwd / cm)	4.45 x 33.66 x 15.24
Unit Weight (lbs.)	3.70
Unit Weight (kg)	1.68
ENVIRONMENTAL	
Storage Temperature Range	-4 to 140 F (-20 to 60 C)
Relative Humidity	0 to 80% RH, Non-Condensing
Operating Temperature	0 to 40C (32 to 104F)
COMMUNICATIONS	
Port Control	Push Buttons
IP Remote Access	No
FEATURES & SPECIFICATIONS	
NIAP-Certified Secure	Yes
Number of Users	1
WARRANTY & SUPPORT	
Product Warranty Period (Worldwide)	3-year limited warranty

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

B002-DUA4