
Silicon Carbide Schottky Diode



V <sub>RRM</sub> =	1200 V
$I_{F(T_{c} = 156^{\circ}C)} =$	10 A
$I_{F(T_c = 156^{\circ}C)} = Q_C =$	32 nC

#### Features

- Gen4 Thin Chip Technology for Low  $V_{\text{F}}$
- Superior Figure of Merit Q<sup>´</sup><sub>C</sub>\*V<sub>F</sub>
- 100% Avalanche (UIL) Tested
- Enhanced Surge Current Withstand Capability
- Temperature Independent Fast Switching
- Low Thermal Resistance
- Positive Temperature Coefficient of VF
- High dV/dt Ruggedness



### Advantages

- Improved System Efficiency
- High System Reliability
- Optimal Price Performance
- Reduced Cooling Requirements
- Increased System Power Density
- Zero Reverse Recovery Current
- Easy to Parallel without Thermal Runaway
- Enables Extremely Fast Switching

#### Applications

- Power Factor Correction (PFC)
- Solar Inverters
- Battery Chargers
- High Frequency Converters
- Switched Mode Power Supply (SMPS)
- AC/DC Power Supplies
- Anti-Parallel / Free-Wheeling Diode
- LED and HID Lighting

Absolute Maximum Ratings	(At T <sub>c</sub> = 25°C Unless Otherwise Stated)
--------------------------	--

Parameter	Symbol	Conditions	Values	Unit	Note
Repetitive Peak Reverse Voltage	V <sub>RRM</sub>		1200	V	
		T <sub>C</sub> = 100°C, D = 1	23		
Continuous Forward Current	IF	T <sub>C</sub> = 135°C, D = 1	16	Α	Fig. 4
		T <sub>C</sub> = 156°C, D = 1	10		
Non-Repetitive Peak Forward Surge Current, Half Sine		T <sub>C</sub> = 25°C, t <sub>P</sub> = 10 ms	80	٨	
Wave	IF,SM	T <sub>C</sub> = 150°C, t <sub>P</sub> = 10 ms	64	А	
Repetitive Peak Forward Surge Current, Half Sine Wave		T <sub>C</sub> = 25°C, t <sub>P</sub> = 10 ms	48	Α	
Repetitive Feak Forward Surge Current, Hall Sille Wave	I <sub>F,RM</sub>	T <sub>C</sub> = 150°C, t <sub>P</sub> = 10 ms	33	A	
Non-Repetitive Peak Forward Surge Current	I <sub>F,MAX</sub>	T <sub>C</sub> = 25°C, t <sub>P</sub> = 10 μs	400	Α	
i <sup>2</sup> t Value	∫i²dt	T <sub>C</sub> = 25°C, t <sub>P</sub> = 10 ms	32	A <sup>2</sup> s	
Non-Repetitive Avalanche Energy	E <sub>AS</sub>	L = 1.8 mH, I <sub>AS</sub> = 10 A	91	mJ	
Diode Ruggedness	dV/dt	V <sub>R</sub> = 0 ~ 960 V	200	V/ns	
Power Dissipation	Ртот	T <sub>C</sub> = 25°C	149	W	Fig. 3
Operating and Storage Temperature	Tj, Tstg		-55 to 175	°C	




## **Electrical Characteristics**

Parameter	Symbol	Conditions		Values		- Unit	Note	
Parallieler	Symbol			Min.	Тур.	Max.	UIII	Note
Diada Farward Valtaga	VF	I <sub>F</sub> = 10 A, T <sub>j</sub> = 25°C			1.5	1.8	V	Fig. 1
Diode Forward Voltage	VF	I <sub>F</sub> = 10 A, T <sub>j</sub> = 175°C			1.9			
Reverse Current	I-	V <sub>R</sub> = 1200 V, T <sub>j</sub> = 25°C			1	10		<b>Fig. 0</b>
	IR	V <sub>R</sub> = 1200 V, T	<sub>j</sub> = 175°C		7		μA	Fig. 2
Total Capacitive Charge	0		V <sub>R</sub> = 400 V		22		nC	Fig. 7
	Qc	I <sub>F</sub> ≤ I <sub>F,MAX</sub> dI <sub>F</sub> /dt = 200 A/µs	V <sub>R</sub> = 800 V		32			
Switching Time	•		V <sub>R</sub> = 400 V		. 10			
	ts	V <sub>R</sub> = 800			< 10		ns	
	0	V <sub>R</sub> = 1 V, f = 1MHz V <sub>R</sub> = 800 V, f = 1MHz			367		<b>ъ</b> Г	Fig. 6
Total Capacitance	С				21		pF	

## Thermal/Package Characteristics


Deremeter	Symbol	Conditions	Values			11	Note
Parameter			Min.	Тур.	Max.	<b>- Unit</b>	Note
Thermal Resistance, Junction - Case	RthJC			1.0		°C/W	Fig. 9
Weight	WT			6.0		g	
Mounting Torque	T <sub>M</sub>	Screws to Heatsink			1.1	Nm	







Rev 21/Jul





Rev 21/Jul





 $I_F = f(V_F, T_j)$ 

### Forward Curve Model Equation:

 $I_F = (V_F - V_{BI})/R_{DIFF} (A)$ 

Built-In Voltage (V<sub>BI</sub>):

$$V_{BI}(T_j) = m \times T_j + n (V)$$
  
m = -0.00119 (V/°C)

n = 1.01 (V)

Differential Resistance (RDIFF):

 $R_{DIFF}(T_j) = a \times T_j^2 + b \times T_j + c (\Omega)$ a = 1.19e-06 (\Omega/°C^2) b = 0.000165 (\Omega/°C) c = 0.049 (\Omega)

Forward Power Loss Equation:

 $P_{LOSS} = V_{BI}(T_j) \times I_{AVG} + R_{DIFF}(T_j) \times I_{RMS}^2$ 




Rev 21/Jul



### Package Dimensions

### TO-247-2 Package Outline



#### NOTE

- 1. CONTROLLED DIMENSION IS INCH. DIMENSION IN BRACKET IS MILLIMETER.
- 2. DIMENSIONS DO NOT INCLUDE END FLASH, MOLD FLASH, MATERIAL PROTRUSIONS.

## GD10MPS12H 1200V 10A SiC Schottky MPS™ Diode



### Compliance

#### **RoHS Compliance**

The levels of RoHS restricted materials in this product are below the maximum concentration values (also referred to as the threshold limits) permitted for such substances, or are used in an exempted application, in accordance with EU Directive 2011/65/EC (RoHS 2), as adopted by EU member states on January 2, 2013 and amended on March 31, 2015 by EU Directive 2015/863. RoHS Declarations for this product can be obtained from your GeneSiC representative.

#### **REACH Compliance**

REACH substances of high concern (SVHCs) information is available for this product. Since the European Chemical Agency (ECHA) has published notice of their intent to frequently revise the SVHC listing for the foreseeable future, please contact a GeneSiC representative to insure you get the most up-to-date REACH SVHC Declaration. REACH banned substance information (REACH Article 67) is also available upon request.

### Disclaimer

GeneSiC Semiconductor, Inc. reserves right to make changes to the product specifications and data in this document without notice. GeneSiC disclaims all and any warranty and liability arising out of use or application of any product. No license, express or implied to any intellectual property rights is granted by this document.

Unless otherwise expressly indicated, GeneSiC products are not designed, tested or authorized for use in life-saving, medical, aircraft navigation, communication, air traffic control and weapons systems, nor in applications where their failure may result in death, personal injury and/or property damage.

### **Related Links**

<ul> <li>SPICE Models</li> </ul>	: https://www.genesicsemi.	com/sic-schottky-mps/GD10	MPS12H/GD10MPS12H_SPICE.zip

- PLECS Models: https://www.genesicsemi.com/sic-schottky-mps/GD10MPS12H/GD10MPS12H\_PLECS.zip
- CAD Models: https://www.genesicsemi.com/sic-schottky-mps/GD10MPS12H/GD10MPS12H\_3D.zip
- · Evaluation Boards: https://www.genesicsemi.com/technical-support
- Reliability: https://www.genesicsemi.com/reliability
- Compliance: https://www.genesicsemi.com/compliance
- Quality Manual: https://www.genesicsemi.com/quality

#### **Revision History**

- Rev 21/Jul: Updated with most recent data
- Supersedes: Rev 21/May



## www.genesicsemi.com/sic-schottky-mps/



Rev 21/Jul Copyright© 2021 GeneSiC Semiconductor Inc. All Rights Reserved. Published by GeneSiC Semiconductor, Inc. 43670 Trade Center Place Suite 155, Dulles, VA 20166; USA Page 7 of 7

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Navitas Semiconductor:

GD10MPS12H