

# PKG.M0.4TL.MN

# **SUMMARY**

#### # Wires

Low voltage

4



Image is for illustrative purpose only

Series	1P
Termination type	Female crimp
IP rating	50
AWG wire size	0.00 - 0.00
Cable Ø	0.00 - 0.00 mm
Status	active
Matching parts	PAG.M0.4TL.AC39N

Download Request a quote Catalog

# **TECHNICAL DETAILS**

#### **Mechanics**

Shell Style/Model	PK*: Fixed receptacle with two nuts (back panel mounting)
Keying	1 key (alpha=0; Plug: male contact; Receptacle: female contact)
Housing Material	PEI (Polyetherimide), black
Variant	N : Black front nut

#### Performance

Configuration	1P.M04 : 4 Low Voltage
Insulator	L: PEEK (UL 94 / V-0/1.5)
Rated Current	8 Amps

#### **Specifications**

Contact Type: Crimp Contact Retention: 24 N Contact Dia.: 0.9 mm (0.0354in) Min. Conductor: 0.5 mm<sup>2</sup> (AWG 20) Max. Conductor: 0.25 mm<sup>2</sup> (AWG 24) R (max): 4.5 mOhm Test voltage (kV rms) Contact-contact: 1.2 Air clearance min.: 1.52 mm Creepage distance min.: 1.52 mm

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

#### Others

Endurance (Shell): >2000 mating cycles Temp (min / max): -50°C / +170°C F ret (min): 50 N F ret (max): 150 N Steam sterilization: > 100 times (with potting on rear connection)

### DRAWINGS



#### Dimensions

	А	Ν	a
mm.	19.5	20.5- 22.2	0-4.5
in.	0,77	0,81	0,00

## **RECOMMENDED BY LEMO**

#### Tools

Crimp Tool:	DPC.91.701.V
Crimp settings:	AWG/Selector = 20-22-24/6-5-5
Positionner:	DCE.91.090.BVM
Extractor:	DCF.91.090.2LT
Replacement contact:	SINGLE: EGG.0B.664.ZZM KIT OF 4: PKG.662.04M

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

### **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

LEMO: PKG.M0.4TL.MN