MABA-010392-CT18A0



1:1 Transmission Line Transformer

5 - 1200 MHz

Rev. V2

Features


- 1:1 Impedance Ratio
- Surface Mount Package
- Excellent Temperature Stability
- Can Be Used on 50 Ω & 75 Ω Systems
- Suitable for all CATV, Broadband and FTTx Applications
- RoHS Compliant & Lead Free
- 260°C Reflow Compatible
- · Available on Tape & Reel

Description

The MABA-010392-CT18A0 is a 1:1 transmission line transformer in a surface mount package.

Ideally suited for all CATV Broadband and FTTx applications.

Functional Schematic



Pin Configuration

Pin #	Function
1	Secondary Dot
2	Not Connected
3	Secondary
4	Primary
5	No Connection
6	Primary Dot

Electrical Specifications: Freq. = 5 - 1200 MHz, $T_A = 25^{\circ}$ C, $Z_0 = 50 \Omega$, $P_{IN} = 0 \text{ dBm}$

Parameter	Frequency (MHz)	Units	Min.	Тур.	Max.
Impedance Ratio	_	dB	_	1:1	_
Insertion Loss 1: (Pin 4-1)	5 - 870 870 - 1000 1000 - 1200	dB	_	-0.4 -0.7 -1.5	-0.7 -1.1 -2.6
Insertion Loss 1: (Pin 4-3)	5 - 870 870 - 1000 1000 - 1200	dB	_	-0.9 -1.2 -2.1	-1.2 -1.6 -3.0
Phase Balance	5 - 1000 1000 - 1200	o	_	2.0 -6.0	±4 ±12
Input Return Loss (Pin 4)	5 - 300 300 - 800 800 - 1200	dB	-15 -10 -5	17 -12 -8	_

Ordering Information

Part number	Description
MABA-010374-CT4A40	2000 piece reel
MABA-010374-CT4ATB	customer evaluation board

Recommended Maximum Ratings

Parameter	Value
Input Power	250 mW
DC Current	200 mA
Operating Temperature	-40°C to +85°C
Storage Temperature	-55°C to +125°C

1

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Visit www.macom.com for additional data sheets and product information.

MABA-010392-CT18A0




1:1 Transmission Line Transformer


5 - 1200 MHz Rev. V2

Typical Performance Curves: $T_A = 25$ °C, $Z_0 = 50 \Omega$, $P_{IN} = 0 \text{ dBm}$

Insertion Loss 1: (Pin 4 to 1)




Insertion Loss 2: (Pin 4 to 3)




Frequency (MHz)


Amplitude Balance



Phase Balance



Return Loss: Input (Pin 4)



Frequency (MHz)




1:1 Transmission Line Transformer


5 - 1200 MHz

Rev. V2


Application Circuit



PCB Layout




Outline Drawing





3.5



- 1. Dimensions in mm.
- 2. Tolerance: ±0.2 mm unless otherwise noted.
- 3. Model number and lot code printed on reel.
- 4. Pin material CuSn6.

Tape & Reel Information

Parameter	Units	Value
Qty per reel	-	2000
Reel Size	mm	330
Tape Width	mm	12.0
Pitch	mm	8.0
Ao	mm	5.6
Во	mm	4.5
Ko	mm	4.0
Orientation	-	F26

MABA-010392-CT18A0



1:1 Transmission Line Transformer

5 - 1200 MHz Rev. V2

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

4

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

MACOM:

MABA-010392-CT18A0