



# Low-Profile Molded Inductor 10µH

#### **APPLICATIONS**



- · Battery-powered devices
- High switching frequency SMPS
- IoT
- Wearable
- Portable devices
- Input filters

#### **FEATURES**

- Size 2.5mmx2.0mmx1.2mm
- Low Profile
- Low Audible Noise
- Molded Construction
- Soft Saturation
- Stable Over High Temperatures
- Low DCR
- Max Operating Temp +125°C
- RoHS/REACH-Compliant, Halogen-Free

# **ELECTRICAL CHARACTERISTICS**

Parameter			Value	Unit
Inductance (1)	L	±20%	10	μH
Resistance	R <sub>DC</sub>	typ	355	mΩ
Resistance MAX	R <sub>DC MAX</sub>	max	400	$\boldsymbol{m\Omega}$
Rated Current (2)	<b>I</b> <sub>R</sub>	typ	1.2	Α
Saturation Current <sub>25°C</sub> (3)	I <sub>SAT 25°C</sub>	typ	1.7	Α
Saturation Current 100°C (4)	I <sub>SAT 100°C</sub>	typ	1.7	Α
Resonance Frequency	fr	typ	16	MHz

#### **GENERAL SPECIFICATIONS**


(1) Inductance	Measured at 100kHz, 100mA
(2) Rated Current	Rated current will cause the coil temperature rise $\Delta T$ of 40K $I_R$ measured with the inductor soldered in a single-layer PCB. Copper layer thickness 35 $\mu$ m Cu / PCB size 30 $x$ 50 $m$ m. Temperature behavior dependent on circuit design, PCB layout, proximity to other components, and trace dimensions and thickness.
(3) Saturation Current 25°C	Saturation current will cause L to drop from 30% at 25°C ambient temperature
(4) Saturation Current 100°C	Saturation current will cause L to drop from 30% at 100°C ambient temperature
Temperature Test Condition	Electrical specifications measured at 25°C, 35% RH if not given differently
Operating Condition	Operating temperature: -40°C to +125°C (including temp rise)
	Should not exceed +125°C under worst-case operation conditions
Storage Condition	Tape and Reel packaging: -10°C to +40°C  Humidity: <50% RH

All MPS parts are lead-free, halogen-free, and adhere to the RoHS directive. For MPS green status, please visit the MPS website under Quality Assurance. "MPS", the MPS logo, and "Simple, Easy Solutions" are registered trademarks of Monolithic Power Systems, Inc. or its subsidiaries.




# **TYPICAL PERFORMANCE CURVES**


### **Temperature Rise vs. Current**




#### **Inductance vs. Current**



Impedance vs. Frequency




Inductance vs. Frequency






# **Quality Factor vs. Frequency**




# AC Resistance vs. Frequency






LAND PATTERN			
Dimensions			
Α	2.1 ref.		
В	0.60 ref.		
С	2.60 ref.		
	(unit in mm)		




# PRODUCT PACKAGE AND DIMENSIONS

# **Dimensions**


(unit in mm)













ORDERING INFORMATION					
Part Number	<b>L</b> (1)	R <sub>DC</sub>	I <sub>R</sub> <sup>(2)</sup>	ISAT 25°C (3)	Isat 100°C <sup>(4)</sup>
	typ (µH)	typ (mΩ)	typ (A)	typ (A)	typ (A)
MPL-AT2512-R33	0.33	13.5	6.4	8.5	8.5
MPL-AT2512-R47	0.47	19	5.5	6.4	6.4
MPL-AT2512-R68	0.68	26	4.7	6	6
MPL-AT2512-1R0	1.0	35	4.0	5.2	5.2
MPL-AT2512-1R5	1.5	56	3.2	4.2	4.2
MPL-AT2514-2R2	2.2	70	2.6	3.4	3.4
MPL-AT2512-3R3	3.3	121	2.0	2.7	2.7
MPL-AT2514-4R7	4.7	180	1.7	2.4	2.4
MPL-AT2512-6R8	6.8	280	1.4	2.2	2.2
MPL-AT2512-100	10	355	1.2	1.7	1.7

GENERAL SPECIFICATIONS		
Measured at 100kHz, 100mA		
Rated current will cause the coil temperature rise $\Delta T$ of 40K $I_R$ measured with the inductor soldered in a single-layer PCB. Copper layer thickness 35 $\mu$ m Cu / PCB size 30 $x$ 50 $\mu$ mm. Temperature behavior dependent on circuit design, PCB layout, proximity to other components, and trace dimensions and thickness.		
Saturation current will cause L to drop from 30% at 25°C ambient temperature		
Saturation current will cause L to drop from 30% at 100°C ambient temperature		
Electrical specifications measured at 25°C, 35% RH if not given differently		
Operating temperature: -40°C to +125°C (including temp rise)		
Should not exceed +125°C under worst-case operation conditions		
Tape and Reel packaging: -10°C to +40°C		
Humidity: <50% RH		

**NOTICE:** The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Monolithic Power Systems (MPS): MPL-AT2512-100