Note: This datasheet may be out of date

Please download the latest datasheet of FDVE0640-H-3R3M# from the official website of Murata Manufacturing

# FDVE0640-H-3R3M#

"#" indicates a package specification code.
















< List of part numbers with package codes > FDVE0640-H-3R3M=P3



### Appearance & Shape







Packaging	Specifications	Minimum Order Quantity
=P3	330Embossed Tape	1000

Mass (typ.)	
1 piece	0.988g



Rated current (Isat) is specified when the decrease of the initial inductance value at 20%. Rated current (Itemp) is specified when temperature of the inductor is raised 40°C by DC current.

1 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Note: This datasheet may be out of date  ${\bf Please\ download\ the\ latest\ data sheet\ of\ FDVE0640-H-3R3M\#\ from\ the\ official\ website\ of\ Murata\ Manufacturing}$ 

### FDVE0640-H-3R3M#

"#" indicates a package specification code.



L size	7.4±0.3mm
W size	6.7±0.3mm
T size	4.0mm
Size code inch (mm)	2926 (7467)
Inductance	3.3µH±20%
Inductance Test Frequency	0.1MHz
Rated current (Isat) (Based on Inductance change)	6000mA
Rated current (Itemp) (Based on Temperature rise)	5600mA
Max. of DC resistance	0.0192Ω
Operating Temperature Range (Self-temperature rise is included)	-40°C to 125°C
Class of magnetic shield	Metal Alloy
Absolute maximum voltage	30Vdc
Series	FDVE0640

2 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





### FDVE0640-H-3R3M#


"#" indicates a package specification code.




The charts below may show another part number which shares its characteristics.







Frequency[Hz]



6000

Current[mA]

8000

10000

12000

FDVE0640-H-3R3M |Z|

FDVE0640-H-3R3M L-Current 20degC

4000

2000

0

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.


Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



Note: This datasheet may be out of date Please download the latest datasheet of FDVE0640-H-3R3M# from the official website of Murata Manufacturing Co., Ltd.

### FDVE0640-H-3R3M#

"#" indicates a package specification code.



4 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



muRata URL : https://www.murata.com/

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

FDVE0640-H-3R3M=P3