

# **Complementary Silicon Power Plastic Transistors** MJE243G (NPN), MJE253G (PNP)

These devices are designed for low power audio amplifier and low-current, high-speed switching applications.

#### **Features**

- High Collector-Emitter Sustaining Voltage
- High DC Current Gain
- Low Collector-Emitter Saturation Voltage
- High Current Gain Bandwidth Product
- Annular Construction for Low Leakages
- These Devices are Pb-Free and are RoHS Compliant\*

#### **MAXIMUM RATINGS**


Rating	Symbol	Value	Unit
Collector-Emitter Voltage	$V_{CEO}$	100	Vdc
Collector-Base Voltage	V <sub>CB</sub>	100	Vdc
Emitter-Base Voltage	V <sub>EB</sub>	7.0	Vdc
Collector Current – Continuous	I <sub>C</sub>	4.0	Adc
Collector Current - Peak	I <sub>CM</sub>	8.0	Adc
Base Current	Ι <sub>Β</sub>	1.0	Adc
Total Power Dissipation @ T <sub>C</sub> = 25°C Derate above 25°C	P <sub>D</sub>	15 120	W mW/°C
Total Power Dissipation  @ T <sub>A</sub> = 25°C  Derate above 25°C	P <sub>D</sub>	1.5 12	W mW/°C
Operating and Storage Junction Temperature Range	T <sub>J</sub> , T <sub>stg</sub>	-65 to +150	°C


Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

## THERMAL CHARACTERISTICS


Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction-to-Case	$R_{\theta JC}$	8.34	°C/W
Thermal Resistance, Junction-to-Ambient	$R_{\theta JA}$	83.4	°C/W

# 4.0 AMPERES POWER TRANSISTORS **COMPLEMENTARY SILICON** 100 VOLTS, 15 WATTS





#### **MARKING DIAGRAM**



= Year WW = Work Week JE2x3 = Device Code x = 4 or 5= Pb-Free Package

### **ORDERING INFORMATION**

Device	Package	Shipping
MJE243G	TO-225 (Pb-Free)	500 Units/Box
MJE253G	TO-225 (Pb-Free)	500 Units/Box

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

1

<sup>\*</sup>For additional information on our Pb-Free strategy and soldering details, please download the onsemi Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

# **ELECTRICAL CHARACTERISTICS** ( $T_C = 25^{\circ}C$ unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit			
OFF CHARACTERISTICS							
Collector-Emitter Sustaining Voltage (I <sub>C</sub> = 10 mAdc, I <sub>B</sub> = 0)	V <sub>CEO(sus)</sub>	100	-	V			
Collector Cutoff Current $(V_{CB} = 100 \text{ Vdc}, I_E = 0)$ $(V_{CE} = 100 \text{ Vdc}, I_E = 0, T_C = 125^{\circ}\text{C})$	I <sub>CBO</sub>	- -	0.1 0.1	μA mA			
Emitter Cutoff Current (V <sub>BE</sub> = 7.0 Vdc, I <sub>C</sub> = 0)	I <sub>EBO</sub>	-	0.1	μAdc			
ON CHARACTERISTICS	•	-	•	•			
DC Current Gain $ \begin{aligned} &(I_C=200 \text{ mAdc, V}_{CE}=1.0 \text{ Vdc}) \\ &(I_C=1.0 \text{ Adc, V}_{CE}=1.0 \text{ Vdc}) \end{aligned} $	h <sub>FE</sub>	40 15	180 -	-			
Collector–Emitter Saturation Voltage ( $I_C$ = 500 mAdc, $I_B$ = 50 mAdc) ( $I_C$ = 1.0 Adc, $I_B$ = 100 mAdc)	V <sub>CE(sat)</sub>	- -	0.3 0.6	V			
Base–Emitter Saturation Voltage (I <sub>C</sub> = 2.0 Adc, I <sub>B</sub> = 200 mAdc)	V <sub>BE(sat)</sub>	-	1.8	V			
Base–Emitter On Voltage (I <sub>C</sub> = 500 mAdc, V <sub>CE</sub> = 1.0 Vdc)	V <sub>BE(on)</sub>	-	1.5	V			
DYNAMIC CHARACTERISTICS	•						
Current-Gain - Bandwidth Product (I <sub>C</sub> = 100 mAdc, V <sub>CE</sub> = 10 Vdc, f <sub>test</sub> = 10 MHz)	f <sub>T</sub>	40	_	MHz			
Output Capacitance (V <sub>CB</sub> = 10 Vdc, I <sub>E</sub> = 0, f = 0.1 MHz)	C <sub>ob</sub>		50	pF			

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.




Figure 1. Power Derating




Figure 2. Switching Time Test Circuit

Figure 3. Turn-On Time




Figure 4. Thermal Response




Figure 5. Active Region Safe Operating Area

There are two limitations on the power handling ability of a transistor: average junction temperature and second breakdown. Safe operating area curves indicate  $I_C - V_{CE}$  limits of the transistor that must be observed for reliable operation; i.e., the transistor must not be subjected to greater dissipation than the curves indicate.

The data of Figure 5 is based on  $T_{J(pk)} = 150^{\circ}\text{C}$ ;  $T_{C}$  is variable depending on conditions. Second breakdown pulse limits are valid for duty cycles to 10% provided  $T_{J(pk)} \le 150^{\circ}\text{C}$ .  $T_{J(pk)}$  may be calculated from the data in Figure 4. At high case temperatures, thermal limitations will reduce the power that can be handled to values less than the limitations imposed by second breakdown.




Figure 6. Turn-Off Time




Figure 7. Capacitance




Figure 8. DC Current Gain




Figure 9. "On" Voltages





Figure 10. Temperature Coefficients







TO-225 CASE 77-09 **ISSUE AD** 

**DATE 25 MAR 2015** 

#### SCALE 1:1





**SIDE VIEW** 

- NOTES: 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. 2. CONTROLLING DIMENSION: MILLIMETERS. 3. NUMBER AND SHAPE OF LUGS OPTIONAL.

	MILLIMETERS			
DIM	MIN	MAX		
Α	2.40	3.00		
A1	1.00	1.50		
b	0.60	0.90		
b2	0.51 0.88			
С	0.39	0.63		
D	10.60	11.10		
E	7.40	7.80		
е	2.04	2.54		
L	14.50 16.63			
L1	1.27	2.54		
P	2.90 3.30			
Q	3.80	4.20		

## **GENERIC MARKING DIAGRAM\***



= Year

ww = Work Week XXXXX = Device Code

= Pb-Free Package

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

STYLE 1: PIN 1. 2., 4. 3.	EMITTER COLLECTOR BASE	STYLE 2: PIN 1. 2., 4. 3.	STYLE 3: PIN 1. 2., 4. 3.	BASE COLLECTOR EMITTER	STYLE 4: PIN 1. 2., 4. 3.	ANODE 1 ANODE 2 GATE	2., 4.	MT 1 MT 2 GATE
STYLE 6: PIN 1. 2., 4. 3.	CATHODE GATE ANODE	STYLE 7: PIN 1. 2., 4. 3.	STYLE 8: PIN 1. 2., 4. 3.	SOURCE GATE DRAIN	STYLE 9: PIN 1. 2., 4. 3.	GATE DRAIN SOURCE	STYLE 10: PIN 1. 2., 4. 3.	SOURCE DRAIN

DOCUMENT NUMBER:	98ASB42049B	Electronic versions are uncontrolled except when accessed directly from the Document Repository Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	TO-225		PAGE 1 OF 1	

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi nakes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

#### ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS:** 

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

onsemi:

MJE243 MJE243G MJE253 MJE253G