# MOSFET – Power, Single N-Channel 40 V, 0.42 mΩ, 554.5 A

#### **Features**

- Small Footprint (8x8 mm) for Compact Design
- Low R<sub>DS(on)</sub> to Minimize Conduction Losses
- Low Q<sub>G</sub> and Capacitance to Minimize Driver Losses
- Wettable Flank Plated for Enhanced Optical Inspection
- AEC-101 Qualified and PPAP Capable
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

#### MAXIMUM RATINGS (T<sub>J</sub> = 25°C unless otherwise noted)

Parameter			Symbol	Value	Unit
Drain-to-Source Voltage			$V_{DSS}$	40	٧
Gate-to-Source Voltage	Э		V <sub>GS</sub>	±20	V
Continuous Drain	Steady State	T <sub>C</sub> = 25°C	I <sub>D</sub>	554.5	Α
Current R <sub>θJC</sub> (Note 2)	State	T <sub>C</sub> = 100°C		392.1	
Power Dissipation	Steady State	T <sub>C</sub> = 25°C	$P_{D}$	245.4	W
R <sub>θJC</sub> (Note 2)	State	T <sub>C</sub> = 100°C		122.7	
Continuous Drain	Steady State	T <sub>A</sub> = 25°C	I <sub>D</sub>	78.9	Α
Current R <sub>0JA</sub> (Notes 1, 2)	State	T <sub>A</sub> = 100°C		55.8	
Power Dissipation	Steady	T <sub>A</sub> = 25°C	$P_{D}$	5.0	W
R <sub>θJA</sub> (Notes 1, 2)	State	T <sub>A</sub> = 100°C		2.5	
Pulsed Drain Current	T <sub>A</sub> = 25	°C, t <sub>p</sub> = 10 μs	I <sub>DM</sub>	900	Α
Operating Junction and Range	Operating Junction and Storage Temperature Range			-55 to +175	°C
Source Current (Body Diode)  Single Pulse Drain-to-Source Avalanche Energy (I <sub>L(pk)</sub> = 52.7 A)  Lead Temperature for Soldering Purposes (1/8" from case for 10 s)			I <sub>S</sub>	204.5	Α
			E <sub>AS</sub>	2058	mJ
			TL	260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

#### THERMAL RESISTANCE MAXIMUM RATINGS

Parameter	Symbol	Value	Unit
Junction-to-Case - Steady State (Note 2)	$R_{\theta JC}$	0.61	°C/W
Junction-to-Ambient - Steady State (Note 2)	$R_{\theta JA}$	30.2	


- 1. Surface-mounted on FR4 board using a 1 in<sup>2</sup> pad size, 1 oz. Cu pad.
- The entire application environment impacts the thermal resistance values shown, they are not constants and are only valid for the particular conditions noted.



#### ON Semiconductor®

#### www.onsemi.com

V <sub>(BR)DSS</sub>	R <sub>DS(ON)</sub> MAX	I <sub>D</sub> MAX
40 V	0.42 m $\Omega$ @ 10 V	5545 A
40 V	0.66 mΩ @ 4.5 V	554.5 A



**N-CHANNEL MOSFET** 



#### **MARKING DIAGRAM**



XXX = Device Code

(8 A-N characters max)
= Assembly Location

WL = 2-digit Wafer Lot Code

Y = Year Code

WW = Work Week Code

#### **ORDERING INFORMATION**

See detailed ordering, marking and shipping information in the package dimensions section on page 5 of this data sheet.

### **ELECTRICAL CHARACTERISTICS** (T<sub>J</sub> = 25°C unless otherwise specified)


Parameter	Symbol	Test Condi	tion	Min	Тур	Max	Unit	
OFF CHARACTERISTICS	-				<u> </u>		-	
Drain-to-Source Breakdown Voltage	V <sub>(BR)DSS</sub>	$V_{GS} = 0 \text{ V}, I_D =$	250 μΑ	40			V	
Drain-to-Source Breakdown Voltage Temperature Coefficient	V <sub>(BR)DSS</sub> / T <sub>J</sub>	I <sub>D</sub> = 250 μA, ref	to 25°C		12.6		mV/°C	
Zero Gate Voltage Drain Current	I <sub>DSS</sub>	$V_{GS} = 0 V$ ,	T <sub>J</sub> = 25°C			10	_	
		$V_{DS} = 40 \text{ V}$	T <sub>J</sub> = 125°C			250	μΑ	
Gate-to-Source Leakage Current	I <sub>GSS</sub>	V <sub>DS</sub> = 0 V, V <sub>GS</sub>	; = 20 V			100	nA	
ON CHARACTERISTICS (Note 3)					•		•	
Gate Threshold Voltage	V <sub>GS(TH)</sub>	$V_{GS} = V_{DS}, I_D =$	= 250 μA	1.2		2.0	V	
Negative Threshold Temperature Coefficient	V <sub>GS(TH)</sub> /T <sub>J</sub>	I <sub>D</sub> = 250 μA, re	f to 25°C		-6.0		mV/°C	
Drain-to-Source On Resistance	R <sub>DS(on)</sub>	V <sub>GS</sub> = 10 V	I <sub>D</sub> = 50 A		0.35	0.42		
		V <sub>GS</sub> = 4.5 V	I <sub>D</sub> = 50 A		0.52	0.66	mΩ	
Forward Transconductance	9FS	V <sub>DS</sub> =5 V, I <sub>D</sub>	= 50 A		323		S	
Gate Resistance	$R_{G}$	T <sub>A</sub> = 25°	С		1.0		Ω	
CHARGES, CAPACITANCES & GATE RESIS	STANCE						1	
Input Capacitance	C <sub>ISS</sub>				16013			
Output Capacitance	C <sub>OSS</sub>	V <sub>GS</sub> = 0 V, f = 1 MHz, V <sub>DS</sub> = 20 V			6801		pF	
Reverse Transfer Capacitance	C <sub>RSS</sub>				299			
Total Gate Charge	Q <sub>G(TOT)</sub>				126			
Threshold Gate Charge	Q <sub>G(TH)</sub>				22.5			
Gate-to-Source Charge	Q <sub>GS</sub>	$V_{GS} = 4.5 \text{ V}, V_{DS} = 20 \text{ V}; I_D = 50 \text{ A}$			39.9		nC	
Gate-to-Drain Charge	$Q_{GD}$				38.4			
Total Gate Charge	Q <sub>G(TOT)</sub>	V <sub>GS</sub> = 10 V, V <sub>DS</sub> = 2	0 V; I <sub>D</sub> = 50 A		265		nC	
SWITCHING CHARACTERISTICS, V <sub>GS</sub> = 4.5	<b>V</b> (Note 4)						1	
Turn-On Delay Time	t <sub>d(ON)</sub>				89.4			
Rise Time	t <sub>r</sub>	Vcs = 4.5 V. Vn	e = 20 V.		111			
Turn-Off Delay Time	t <sub>d(OFF)</sub>	$V_{GS} = 4.5 \text{ V}, V_{D}$ $I_{D} = 50 \text{ A}, R_{G}$	= 6 Ω		180		ns	
Fall Time	t <sub>f</sub>				84.7			
DRAIN-SOURCE DIODE CHARACTERISTIC	S						I	
Forward Diode Voltage	$V_{SD}$	V <sub>GS</sub> = 0 V,	T <sub>J</sub> = 25°C		0.75	1.2		
		I <sub>S</sub> = 50 A	T <sub>J</sub> = 125°C		0.6		V	
Reverse Recovery Time	t <sub>RR</sub>		•		99.3		ns	
Charge Time	t <sub>a</sub>	$V_{GS} = 0 \text{ V. dIS/dt}$	= 100 A/us.		62.4			
Discharge Time	t <sub>b</sub>	$V_{GS} = 0 \text{ V, dIS/dt} = 100 \text{ A/}\mu\text{s,}$ $I_{S} = 50 \text{ A}$			36.9		1	
Reverse Recovery Charge	Q <sub>RR</sub>				228		nC	

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

3. Pulse Test: pulse width  $\leq 300~\mu s$ , duty cycle  $\leq 2\%$ .

4. Switching characteristics are independent of operating junction temperatures.

#### **TYPICAL CHARACTERISTICS**






Figure 2. Transfer Characteristics




Figure 3. On-Resistance vs. Gate-to-Source Voltage




Figure 4. On-Resistance vs. Drain Current and Gate Voltage




Figure 5. On–Resistance Variation with Temperature




Figure 6. Drain-to-Source Leakage Current vs. Voltage

#### **TYPICAL CHARACTERISTICS**




Figure 7. Capacitance Variation




Figure 8. Gate-to-Source Voltage vs. Total Charge




Figure 9. Resistive Switching Time Variation vs. Gate Resistance




Figure 10. Diode Forward Voltage vs. Current




Figure 11. Maximum Rated Forward Biased Safe Operating Area




Figure 12.  $I_{\mbox{\scriptsize PEAK}}$  vs. Time in Avalanche

#### **TYPICAL CHARACTERISTICS**





Figure 13. Thermal Characteristics


#### **DEVICE ORDERING INFORMATION**


Device	Marking	Package	Shipping <sup>†</sup>
NVMTS0D6N04CLTXG	0D6N04CL	POWER 88 (Pb-Free)	3000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.









DIM	MILLIMETERS		
Di.v.	MIN.	MAX.	
Α	1.00	1.10	1.20
A1	0.00	-	0.05
b	0.90	1.00	1.10
b1	0.35	0.45	0.55
C	0.23	0.28	0.33
D	8.20	8.30	8.40
D1	7.90	8.00	8.10
D2	6.80	6.90	7.00
D3	6.90	7.00	7.10
Ш	8.30	8.40	8.50
E1	7.80	7.90	8.00
E2	5.24	5.34	5.44
E3	0.25	0.35	0.45
е		2.00 BS	С
e/2		1.00 BS	С
e1		2.70 BS	С
e1/2	1.35 BSC		
K	1.50	1.57	1.70
٦	0.64	0.74	0.84
L1	0.67	0.77	0.87
θ	0°		12°

*FOR ADDITIONAL INFORMATION ON OUR PB-FREE	
STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLO	ΑD
THE ONSEMI SOLDERING AND MOUNTING TECHNIQUES	
REFERENCE MANUAL, SOLDERRM/D.	

CITOTIEST AND COLDERNING DETAILS, I LEAGE DOWNLOAD
THE ONSEMI SOLDERING AND MOUNTING TECHNIQUES
REFERENCE MANUAL, SOLDERRM/D.

DESCRIPTION.	TDFNW8 8.30x8.40x1.10, 2	· · ·		
DOCUMENT NUMBER:	98AON80534G	BAON80534G Electronic versions are uncontrolled except when accessed directly from the Printed versions are uncontrolled except when stamped "CONTROLLED C		


onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

#### TDFNW8 8.30x8.40x1.10, 2.00P

CASE 507AP ISSUE E

**DATE 08 MAY 2024** 

# GENERIC MARKING DIAGRAM\*



XXXX = Specific Device Code
A = Assembly Location
WL = Wafer Lot Code
Y = Year Code
WW = Work Week Code

\*This information is generic. Please refer to device data sheet for actual part marking. Pb–Free indicator, "G" or microdot " •", may or may not be present. Some products may not follow the Generic Marking.

DOCUMENT NUMBER:	98AON80534G	Electronic versions are uncontrolled except when accessed directly fron Printed versions are uncontrolled except when stamped "CONTROLLED		
DESCRIPTION:	TDFNW8 8.30x8.40x1.10, 2.00P		PAGE 2 OF 2	

onsemi and ONSEMi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

#### ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS:** 

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

onsemi:

NVMTS0D6N04CLTXG