

Contact insert - HC-B 10-ESTQ-2,5-OLOGO - 1605629

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Male insert, 10-pos., QUICKON connection, marking 1-x



Key Commercial Data

Packing unit	10 pc
Minimum order quantity	10 pc
GTIN	4 017918 940836
GTIN	4017918940836

Technical data

Ambient conditions

A self-self-second self-self-self-self-self-self-self-self-	40 °C 125 °C
Ambient temperature (operation)	-40 °C 125 °C
	•

General

Note	For HEAVYCON ADVANCE and HEAVYCON housing of B10 type. Coding using the CP-HC (1686478) coding profile. HC-B6/ HC-B10 for two coding profiles. HC-B16/ HC-B24 for 4 coding profiles. Connectors may be operated only when there is no load/voltage.
	Connectors may be operated only when there is no load/voltage.
Size	В
Number of positions	10
Flammability rating according to UL 94	V0
Assembly instructions	To ensure correct use, installation in housing with IP54 protection or better is required
Connection	For housings of type B10. Connectors may only be actuated when there is no load/voltage.


Standards and Regulations

Flammability rating according to UL 94	V0




Contact insert - HC-B 10-ESTQ-2,5-OLOGO - 1605629

Drawings



Dimensional drawing






Male insert

The figure shows the derating diagram of various series B contact inserts (B6 to B24), conductor cross section 2.5 mm²

Dimensional drawing



Mounting cutout when used without housing

Approvals

Approvals

Approvals

EAC

Ex Approvals

Approval details

EAC

EHE

RU C-DE.Al30.B.01102



Phoenix Contact 2018 © - all rights reserved http://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstr. 8 32825 Blomberg Germany Tel. +49 5235 300

Fax +49 5235 3 41200

http://www.phoenixcontact.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Phoenix Contact: 1605629