Small Signal Transistors

TO-39 Case (Continued)



| TYPE NO. | DESCRIPTION | V _{CBO} | V _{CEO} | V _{EBO} | I _{CBO} | @ V _{CB} | hF | E | @I _C | @ V _{CE} | V _{CE(SA} | т) ^{@ I} с | fT | Cob | ton | t _{off} | NF |
|----------------|------------------|------------------|-------------------|------------------|---------------------|-------------------|------------------|------------|-----------------|-------------------|--------------------|---------------------|--------------|----------|------------|------------------|------|
| | | (V) | (V) | (V) | (µA) | (V) | | | (mA) | (V) | (V) | (mA) | (MHz) | (pF) | (ns) | (ns) | (dB) |
| | | | *V _{CER} | | *ICEO **ICES | | | | | | | | *TYP †TYP | *TYP | *TYP | *TYP | *TYP |
| | | | | | ***ICEV ****ICER | | | | | | | | in GHz | | | | |
| 2N5784 | NPN AMPL/SWITCH | MIN 80 | MIN 65 | MIN 5.0 | 10*** | 75 | MIN 20 | MAX 150 | 1,000 | 2.0 | MAX 0.50 | 1,000 | MIN 1.0 | MAX | MAX | MAX | MAX |
| 2N5785 | NPN AMPL/SWITCH | 65 | 50 | 5.0 | 10*** | 60 | 20 | 100 | 1,200 | 2.0 | 0.50 | 1,200 | 1.0 | | | | |
| 2N5786 | NPN AMPL/SWITCH | 45 | 40 | 3.5 | 10*** | 45 | 20 | 150 | 1,600 | 2.0 | 1.00 | 1,600 | 1.0 | | 5.0 | 15 | |
| 2N5859 | NPN CORE DRIVER | 80 | 40 | 6.0 | 0.25 | 50 | 30 | 120 | 500 | 1.0 | 0.70 | 1,000 | 250 | 7.0 | 35 | 60 | |
| 2N5861 | NPN CORE DRIVER | 100 | 50 | 6.0 | 0.20 | 50 | 25 | 100 | 500 | 1.0 | 0.50 | 500 | 200 | 7.0 | 25 | 60 | |
| 2N6190 | NPN HIGH CURRENT | 80 | 80 | 6.0 | 10 | 80 | 30 | 120 | 2,000 | 2.0 | 0.30 | 2,000 | 30 | 300 | 25 | | |
| 2N6191 | PNP HIGH CURRENT | 80 | 80 | 6.0 | 10 | 80 | 60 | 240 | 2,000 | 2.0 | 0.70 | 2,000 | 30 | 300 | | | |
| 2N6192 | PNP HIGH CURRENT | 100 | 100 | 6.0 | 10 | 100 | 30 | 120 | 2,000 | 2.0 | 0.70 | 2,000 | 30 | 300 | | | |
| 2N6192 | PNP HIGH CURRENT | 100 | 100 | 6.0 | 10 | 100 | 60 | 240 | 2,000 | 2.0 | 0.70 | 2,000 | 30 | 300 | | | |
| BC140 | NPN AMPL/SWITCH | 80 | 40 | 7.0 | 0.10** | 60 | 40 | 240 250 | l ' | | 1.00 | 1,000 | 50 | | 250 | | |
| | | | | | | | | | 100 | 1.0 | | , | | 25 | | 850 | |
| BC141 BC160 | NPN AMPL/SWITCH | 100 40 | 60 40 | 7.0 5.0 | 0.10** 0.10** | 60 40 | 40 40 | 250 250 | 100 100 | 1.0 1.0 | 1.00 1.00 | 1,000 | 50 50 | 25 30 | 250 500 | 850 650 | |
| | | | | | | | | | | | | , | | | | | |
| BC161 BC300 | PNP AMPL/SWITCH | 60 120 | 60 80 | 5.0 7.0 | 0.10** | 60 60 | 40 40 | 250 240 | 100 150 | 1.0 | 1.00 0.50 | 1,000 150 | 50 100* | 30 | 500 | 650 | |
| | | | | - | 0.02 | | | | | 10 | | | | 12* | | | |
| BC301 | NPN AMPL/SWITCH | 90 | 60 | 7.0 | 0.02 | 60 | 40 | 240 | 150 | 10 | 0.50 | 150 | 100* | 12* | | | |
| BC302 | NPN AMPL/SWITCH | 60 | 45 | 7.0 | 0.02 | 60 | 40 | 240 | 150 | 10 | 0.50 | 150 | 100* | 12* | | | |
| BC303 | PNP AMPL/SWITCH | 85 | 60 | 6.0 | 0.02 | 60 | 40 | 240 | 150 | 10 | 0.65 | 150 | 100* | 15* | | | |
| BC304 | PNP AMPL/SWITCH | 60 | 45 | 6.0 | 0.02 | 60 | 40 | 240 | 150 | 10 | 0.65 | 150 | 100* | 15* | | | |
| BC440 | NPN AMPL/SWITCH | 50 | 40 | 5.0 | 0.10 | 40 | 40 | 250 | 500 | 4.0 | 1.00 | 1,000 | 50 | | | | |
| BC441 | NPN AMPL/SWITCH | 70 | 60 | 5.0 | 0.10 | 40 | 40 | 250 | 500 | 4.0 | 1.00 | 1,000 | 50 | | | | |
| BC460 | PNP AMPL/SWITCH | 50 | 40 | 5.0 | 0.10 | 40 | 40 | 250 | 500 | 4.0 | 1.00 | 1,000 | 50 | | | | |
| BC461 | PNP AMPL/SWITCH | 70 | 60 | 5.0 | 0.10 | 40 | 40 | 250 | 500 | 4.0 | 1.00 | 1,000 | 50 | | | | |
| BCW78 | NPN AMPL/SWITCH | 45 | 45 | 5.0 | 0.02** | 45 | 100 | 630 | 100 | 1.0 | 0.70 | 500 | | | | | |
| BCW80 | PNP AMPL/SWITCH | 45 | 45 | 5.0 | 0.02** | 45 | 63 | 400 | 100 | 1.0 | 0.70 | 500 | | | | | |
| BD115 | NPN HIGH VOLTAGE | 250 | 180 | 5.0 | 550* | 200 | 22 | | 50 | 100 | 9.00 | 100 | 150* | | | | |
| BF178 | NPN AMPL/SWITCH | 185 | 115 | 5.0 | 0.01 | 185 | 20 | | 30 | 20 | | | 120* | | | | |
| BF257 | NPN HIGH VOLTAGE | 160 | 160 | 5.0 | 50 | 100 | 25 | | 30 | 10 | 1.00 | 30 | 90* | | | | |
| BF258 | NPN HIGH VOLTAGE | 250 | 250 | 5.0 | 50 | 200 | 25 | | 30 | 10 | 1.00 | 30 | 90* | | | | |
| BF259 | NPN HIGH VOLTAGE | 300 | 300 | 5.0 | 50 | 250 | 25 | | 30 | 10 | 1.00 | 30 | 90* | | | | |
| BF337 | NPN HIGH VOLTAGE | 250 | 200 | 5.0 | 100**** | 200 | 20 | | 30 | 10 | | | | | | | |
| BFR36 | NPN AMPL/SWITCH | 40 | 30 | 3.0 | 0.15 | 20 | 60 | | 70 | 5.0 | | | 1.0 | | | | 4.0* |
| BFS89 | NPN HIGH VOLTAGE | 300 | 300 | 5.0 | 0.05 | 250 | 25 | | 50 | 10 | | | | | | | |
| BFS95 | PNP AMPL/SWITCH | 40 | 35 | 6.0 | 0.05 | 30 | 15 | | 1,000 | 10 | 0.20 | 150 | | | | | |
| BFT28C | PNP HIGH VOLTAGE | 300 | 250 | | 5.00 | 150 | 20 | | 10 | 10 | 5.00 | 30 | 25 | | | | |
| BFW16A | NPN AMPL/SWITCH | 40 | 25 | 3.0 | 20 | 20 | 25 | | 50 | 5.0 | | | 1.2† | | | | 6.0 |
| BFW44 | PNP AMPL/SWITCH | 150 | 150 | 6.0 | 0.01 | 100 | 40 | | 10 | 10 | 0.50 | 10 | 60 | 7.0 | | | |
| BFX34 | NPN AMPL/SWITCH | 120 | 60 | 6.0 | 10** | 60 | 40 | 150 | 2,000 | 2.0 | 1.00 | 5,000 | 70 | 100 | 600 | 1,200 | |
| BFX84 | NPN AMPL/SWITCH | 100 | 60 | 6.0 | 0.50 | 100 | 30 | | 150 | 10 | 1.00 | 500 | 50 | 12 | | | |
| BFX85 | NPN AMPL/SWITCH | 100 | 60 | 6.0 | 0.50 | 100 | 70 | | 150 | 10 | 1.00 | 500 | 50 | 12 | | | TM |

(26-September 2011)



OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- · Consolidated shipping options

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities

Special wafer diffusions

· Custom product packing

- PbSn plating options
- Package details
- Application notes
- · Application and design sample kits

Custom bar coding for shipments

Custom product and package development

REQUESTING PRODUCT PLATING

- 1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
- If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp. 145 Adams Avenue Hauppauge, NY 11788 USA Main Tel: (631) 435-1110 Main Fax: (631) 435-1824 Support Team Fax: (631) 435-3388 www.centralsemi.com

Worldwide Field Representatives: www.centralsemi.com/wwreps

Worldwide Distributors: www.centralsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: <u>www.centralsemi.com/terms</u>





http://www.centralsemi.com

Product End of Life Notification

| PDN ID: | PDN01239 |
|--------------------|----------|
| Notification Date: | 7/29/22 |
| Last Buy Date: | 1/29/23 |
| Last Shipment Date | 7/29/23 |

Summary: The following NPN high current transistors in the TO-39 package are discontinued now classified as of End of Life (EOL).

Although Central Semiconductor Corp. makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by other manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's ongoing Product Portfolio Management. Any replacement products are noted below. The effective date for placing last purchase orders will be six (6) months from the date of this notice and twelve (12) months from the notice date for final shipments, and minimum order quantities may apply. The last purchase and shipment dates may be extended if inventory is available.

* All Plating types (PBFREE,TIN/LEAD) for each item listed are included in this notice.

| Central Part Number | Suggested Replacement |
|---------------------|-----------------------|
| BFX34 | N/A |
| BSX62-10 | N/A |
| BSX63-10 | N/A |
| 2N3420 | N/A |
| 2N3421 | N/A |
| 2N3507 | N/A |
| 2N4237 | N/A |
| 2N4238 | N/A |
| 2N4239 | N/A |
| 2N4895 | N/A |
| 2N5784 | N/A |
| 2N5785 | N/A |

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. If you would like assistance, please visit https://my.centralsemi.com/submit-inquiry?type=ER to submit an online inquiry.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



Product End of Life Notification

| PDN ID: | PDN01114 |
|--------------------|------------|
| Notification Date: | 9/06/19 |
| Last Buy Date: | Stock Only |
| Last Shipment Date | Stock Only |

http://www.centralsemi.com

Please be advised that Central Semiconductor must immediately discontinue the product(s) listed in the attached PDN notice. We are unable to accept any further orders for these products **unless** we have available inventory on hand.

You may have purchased one or more of the products listed. Please do not hesitate to contact your local Central Semiconductor sales representative with any questions or needs you may have. Central regrets any inconvenience this may cause.

Sincerely,

Central Semiconductor Corp.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



Product End of Life Notification

PDN ID:PDN01114Notification Date:9/06/19Last Buy Date:Stock OnlyLast Shipment DateStock Only

Summary: The CP616, CP617, CP618, CP223, CP229 and CP243 RF transistor die processes are discontinued and now classified and End of Life (EOL).

Although Central Semiconductor Corp. makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by other manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's ongoing Product Management Process. Any replacement products are noted below. The effective date for placing last purchase orders will be six (6) months from the date of this notice and twelve (12) months from the notice date for final shipments, and minimum order quantities may apply. The last purchase and shipment dates may be extended if inventory is available.

| Central Part Number | Replacement |
|---------------------|-----------------|
| BFW16A | N/A, Stock Only |
| CEN1179 | N/A, Stock Only |
| CEN5503 | N/A, Stock Only |
| CM4957 | N/A, Stock Only |
| CM5160 | N/A, Stock Only |
| CM5583 | N/A, Stock Only |
| CM5943 | N/A, Stock Only |
| CP223-2N3866-CT | N/A, Stock Only |
| CP223-2N3866-WN | N/A, Stock Only |
| CP229-2N5109-CM | N/A, Stock Only |
| CP229-2N5109-CT | N/A, Stock Only |
| CP229-2N5109-CT20 | N/A, Stock Only |
| CP229-2N5109-WN | N/A, Stock Only |
| CP243-CM5943-WN | N/A, Stock Only |
| CP616-CM5160-CT | N/A, Stock Only |
| CP616-CM5160-CT20 | N/A, Stock Only |
| CP616-CM5160-WN | N/A, Stock Only |
| CP616-2N5160-CM | N/A, Stock Only |
| CP616-2N5160-CT | N/A, Stock Only |
| CP616-2N5160-WN | N/A, Stock Only |
| CP617-CEN1271-CM | N/A, Stock Only |
| CP617-CEN1271-CT | N/A, Stock Only |
| CP617-CEN1271-WN | N/A, Stock Only |
| CP617-CM4957-CM | N/A, Stock Only |
| CP617-CM4957-CT | N/A, Stock Only |
| CP617-CM4957-CT20 | N/A, Stock Only |
| CP617-CM4957-WN | N/A, Stock Only |
| CP618-CM5583-CT | N/A, Stock Only |
| CP618-CM5583-WN | N/A, Stock Only |
| CP618-2N5583-WN | N/A, Stock Only |
| 2N3866 | N/A, Stock Only |
| 2N3866 TRAY | N/A, Stock Only |
| 2N3866A | N/A, Stock Only |
| 2N4427 | N/A, Stock Only |
| 2N5109 | N/A, Stock Only |
| 2N5109UB BK | N/A, Stock Only |
| | |

*** CONTINUED ***

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



Product End of Life Notification

| PDN ID: | PDN01114 |
|--------------------|------------|
| Notification Date: | 9/06/19 |
| Last Buy Date: | Stock Only |
| Last Shipment Date | Stock Only |

http://www.centralsemi.com

Please be advised that Central Semiconductor must immediately discontinue the product(s) listed in the attached PDN notice. We are unable to accept any further orders for these products **unless** we have available inventory on hand.

You may have purchased one or more of the products listed. Please do not hesitate to contact your local Central Semiconductor sales representative with any questions or needs you may have. Central regrets any inconvenience this may cause.

Sincerely,

Central Semiconductor Corp.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



http://www.centralsemi.com

Product End of Life Notification

| PDN ID: | PDN01114 |
|--------------------|------------|
| Notification Date: | 9/06/19 |
| Last Buy Date: | Stock Only |
| Last Shipment Date | Stock Only |

*** CONTINUED FROM PRIOR PAGE ***

Central Part Number Replacement

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. Please email your requests to engineering@centralsemi.com.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Central Semiconductor: 2N5785 PBFREE 2N5786 PBFREE