



# 450VA 240W Line-Interactive UPS with 4 Outlets - AVR, VS Series, 120V, 50/60 Hz, Tower

### MODEL NUMBER: VS450T



Line-interactive UPS provides basic battery backup with AVR protection for your office computer, home theater setup or digital signage.

#### Features

**450VA/240W/120V Battery Backup for PCs, Home Theater or Digital Signage**This 120V UPS with AVR protection provides reliable battery backup and AC power protection against blackouts, brownouts, surges and line noise that can damage valuable electronics or destroy data. The four-outlet 120V battery backup is ideal protection for your home office, media center or commerce components, including computers, routers, printers, HDTVs, Blu-ray players, game consoles, ATMs, security systems and digital signage equipment.

Allows Time to Back Up Critical Files During a BlackoutBackup support allows you to work through short power failures, and gives you enough time to safely save files and shut down your system in case of a prolonged blackout. Backup time varies according to load, but the line-interactive UPS system should keep an energy-efficient desktop computer with small LCD monitor powered as long as 17 minutes. During normal operation, incoming utility power keeps the replaceable internal battery fully charged, so backup power will always be available.

**Connects Your Equipment to 4 NEMA 5-15R Outlets**Three 5-15R outlets provide both battery backup and surge protection for your computer, monitor and other crucial components. The other 5-15R outlet is surge-protected only for printers, scanners and other non-essential equipment. A high 95% line mode efficiency rating reduces BTU emissions, energy consumption and, ultimately, your energy costs.

Automatic Voltage Regulation (AVR) Corrects Low-Voltage ConditionsAVR protects your equipment from incremental hardware damage, data loss and performance problems caused by brownouts. The VS450T can correct brownouts as low as 89V and overvoltages as high as 145V back to nominal 120V power without drawing on the battery backup needed to support your equipment during a blackout.

**316 Joules Fight Back Against Unexpected Power Surges**A 316-joule surge suppression rating protects connected components from the harmful effects of power surges.

**Combats Electromagnetic Interference That Can Harm Equipment**Various electromagnetic and radio sources found in virtually every home and business can cause disruptive interference on the AC line. Known as EMI (electromagnetic interference) and RFI (radio frequency interference), this line noise is a common cause of performance problems and can lead to incremental hardware damage, data corruption and audio/video transmission problems. The VS450T incorporates technology that filters out disruptive line noise so that it won't affect your equipment.

#### **Highlights**

- Protects valuable equipment from dangers posed by brownouts, surges and line noise
- AVR battery backup allows time to save files and safely shut down during blackouts
- 4 NEMA 5-15R outlets provide power to PC, home theater or digital signage equipment
- Alarm and front-panel LEDs report online, battery, fault and overload conditions
- High 95% efficiency with low BTU ratings saves power and lowers your energy costs

#### **Applications**

- Protect your PC and other sensitive electronics against power surges, brownouts and blackouts
- Operate essential equipment during short-term power outages using battery backup power
- Shut down PCs, DVRs, routers and other equipment without data loss during long-term power outages

#### **Package Includes**

- VS450T 450VA 240W Line-Interactive UPS with 4 Outlets
- Owner's manual



**Easy-to-Read LEDs Report Real-Time UPS and Power Status**Three front-panel LED indicators monitor essential information, such as online, battery and fault modes. An audible alarm will sound in case of low battery, excessive load and fault condition.

**Tower Form Factor for Easy Placement in Your Workspace or Media Center**The long-lasting ABS housing fits easily on a desktop, shelf or anywhere else convenient to your workstation or home theater. The five-foot power cord with NEMA 5-15P plug connects to a properly grounded AC wall outlet.

### **Specifications**

OVERVIEW		
UPC Code	037332212887	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	5A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
Input Circuit Breakers	5A	
UPS Input Cord Length (ft.)	5	
UPS Input Cord Length (m)	1.5	
Recommended Electrical Service	15A 120V	
OUTPUT		
Output Capacity (VA)	450	
Output Capacity (kVA)	0.45	
Output Capacity (Watts)	240	
Output Capacity (kW)	0.24	
Output Capacity Details	3.8A @ 120V. (LINE MODE) 110%+/- 10% @ 5 minutes; (BATTERY MODE) 110% +/- 10% @ 5 seconds	
Power Factor	0.53	
Nominal Voltage Details	120V sinusoidal in line mode and 120V PWM in battery mode	
Frequency Compatibility	60 Hz	
Frequency Compatibility Details	Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal.	
Output Voltage Regulation (Line Mode)	120V (+9%, -12%)	
Output Voltage Regulation (Battery Mode)	120V (+/- 10%)	
UPS Output Receptacles (Surge Suppression Only)	3 UPS outlets, 1 surge-only outlet	
Output AC Waveform (AC Mode)	Sine wave	





Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Output Receptacles	(4) 5-15R	
Individually Controllable Load Banks	No	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Runtime Full Load (min.)	0.5 min. (240W)	
Runtime Half Load (min.)	5 min. (120W)	
Expandable Runtime	No	
DC System Voltage (VDC)	12	
Battery Recharge Rate (Included Batteries)	8 hours (10% to 90%)	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 89 to 145	
Overvoltage Correction	Input voltages between 132 and 145 are reduced by 15%	
Undervoltage Correction	Input voltages between 89 and 108 are boosted by 18%	
USER INTERFACE, ALERTS & CON	ITROLS	
Switches	Controls off/on power status	
Audible Alarm	Audible alarm indicates low-battery, fault, overload and replace-battery status	
LED Indicators	3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red)	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	316	
UPS AC Suppression Joule Rating UPS AC Suppression Response Time	316 Instantaneous	
UPS AC Suppression Response		
UPS AC Suppression Response Time	Instantaneous	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression	Instantaneous	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL	Instantaneous Yes	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor	Instantaneous Yes Tower	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor Installation Form Factors Supported with Included Accessories	Instantaneous         Yes         Tower         Tower	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor Installation Form Factors Supported with Included Accessories Primary UPS Depth (mm)	Instantaneous Yes Tower Tower 300	
UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor Installation Form Factors Supported with Included Accessories Primary UPS Depth (mm) Primary UPS Height (mm)	Instantaneous Yes Tower Tower 300 142	





r		
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, in.)	5.6 x 4 x 11.8	
UPS Power Module Weight (kg)	3.72	
UPS Power Module Weight (lbs.)	8.2	
Unit Weight (lbs.)	8.200	
Unit Weight (kg)	3.72	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	5° to 113°F (-15° to 45°C )	
Relative Humidity	0 to 90%, non-condensing	
AC Mode BTU / Hr. (Full Load)	23	
AC Mode Efficiency Rating (100% Load)	95%	
AC Economy Mode Efficiency Rating (100% Load)	0.95	
Operating Elevation	0-6562 ft. (0-2000 m)	
COMMUNICATIONS		
Network Management Card Description	Network management not supported	
Communications Interface	None	
LINE / BATTERY TRANSFER		
Transfer Time	6 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	89	
High Voltage Transfer to Battery Power (Setpoint)	145	
FEATURES & SPECIFICATIONS		
High Availability UPS Features	Automatic Voltage Regulation (AVR); Surge/noise protection	
APPLICATIONS		
UPS Applications	Home/Office Desktop; Retail/Point of Sale; Hospitality	
STANDARDS & COMPLIANCE		
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778	
Product Compliance	RoHS; FCC Part 15 Class A (USA)	
WARRANTY & SUPPORT		





Product Warranty Period (U.S. & Canada)	3-year limited warranty
Product Warranty Period (Latin America)	3-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	3-year limited warranty

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

<u>VS450T</u>